ML-TDR-64-151
PART II

AD0629740 OFFICIAL FILE COPY

C-164

THEORETICAL STUDIES ON THE DEGRADATION OF LADDER POLYMERS

PART II. VAPORIZATION STUDIES

MARTIN M. TESSLER, 1/LT., USAF

TECHNICAL REPORT ML-TDR-64-151, PART II

DECEMBER 1965

AIR FORCE MATERIALS LABORATORY
RESEARCH AND TECHNOLOGY DIVISION
AIR FORCE SYSTEMS COMMAND
WRIGHT-PATTERSON AIR FORCE BASE, OHIO

OFFICIAL FILE COPY

Distribution of this document is unlimited.

20040225203

BEST AVAILABLE COPY

NOTICES

When Government drawings, specifications, or other data are used for any purpose other than in connection with a definitely related Government procurement operation, the United States Government thereby incurs no responsibility nor any obligation whatsoever; and the fact that the Government may have formulated, furnished, or in any way supplied the said drawings, specifications, or other data, is not to be regarded by implication or otherwise as in any manner licensing the holder or any other person or corporation, or conveying any rights or permission to manufacture, use, or sell any patented invention that may in any way be related thereto.

Copies of this report should not be returned to the Research and Technology Division unless return is required by security considerations, contractual obligations, or notice on a specific document.

THEORETICAL STUDIES ON THE DEGRADATION OF LADDER POLYMERS

PART II. VAPORIZATION STUDIES

MARTIN M. TESSLER, 1/LT., USAF

Distribution of this document is unlimited.

FOREWORD

This report was prepared by the Polymer Branch of the Nonmetallic Materials Division. The work was initiated under Project No. 7342, "Fundamental Research on Macromolecular Materials and Lubrication Phenomena," Task No. 734203, "Fundamental Principles Determining the Behavior of Macromolecules." It was administered under the direction of the AF Materials Laboratory, Research and Technology Division, 1stLt Martin M. Tessler, project engineer.

This report covers work conducted from January 1964 to December 1964. The manuscript was released by the author in May 1965 for publication as an RTD technical report.

This technical report has been reviewed and is approved.

WILLIAM E, GIBBS

Chief, Polymer Branch

Wieen ? Sis

Nonmetallic Materials Division Air Force Materials Laboratory

ABSTRACT

The random degradation of four and six-membered ring ladder polymers were investigated by means of a digital computer and the results compared to a single chain polymer undergoing degradation under identical conditions. The percent vaporization versus time and the rate of weight loss versus time was plotted and significant differences were obtained. The results indicate that ladder polymers should have increased stability over single chain polymers undergoing random degradation.

TABLE OF CONTENTS

	PAGE
INTRODUCTION	1
MONTE CARLO MODEL	2
RESULTS	4
REFERENCES	5
APPENDIXES I THROUGH V - COMPUTER PROGRAM	1-52


ILLUSTRATIONS

FIGURE		PAGE
1.	Ladder Polymer Model	2
2.	Plot of Percent Vaporization Versus Time for Simple Case Ladder Polymers Undergoing Random Degradation	6
3.	Plot of Percent Vaporization Versus Time for Complex Case Ladder Polymers Undergoing Random Degradation	7
4.	Plot of Rate of Weight Loss Versus Time for Simple Case Ladder Polymers Undergoing Random Degradation	8
5.	Plot of Rate of Weight Loss Versus Time for Complex Case Ladder Polymers Undergoing Random Degradation	9


INTRODUCTION

Previously (Reference 1), the thermal stability of a ladder polymer undergoing random degradation was compared with that of a single chain polymer by using a digital computer to set up a statistical (Monte Carlo) model of the degrading system. The change in molecular weight versus time was plotted and significant differences were found in the shapes of the curves for the ladder polymers as compared to a single chain polymer.

A common test for thermal stability of a polymer is to measure its loss of weight upon heating. The previous report (Reference 1) studies the changes in molecular weight of a ladder polymer undergoing random degradation upon heating in a closed system where no weight loss has occurred. The present report discusses the random degradation of a ladder polymer in an open system where, upon heating, small molecular weight fragments of the polymer are vaporized out of the system. Two types of ladder polymers are studied. Type I is a fused four-membered ring and Type II is a fused six-membered ring. All of the results for a four-membered ring are equally applicable to an eight-membered ring.



TYPE I



TYPE II

Initially, a simplified scheme of degradation was considered where a broken bond can break a molecule only if the bond opposite it is broken. The much more realistic scheme of random degradation, where breaks in the crosslinks will result in increased molecule breaks, was also considered. This is called the complex case of degradation.

The following assumptions were made in defining the degrading system:

- 1. The polymer sample is initially monodisperse; that is, only chains of a single length are present.
- 2. All bonds in the polymer chain are of equal strength and accessibility, regardless of the length of the chain and the positions of the bonds in the molecule.
- 3. The rate of bonds breaking is proportional to the number of unbroken bonds in the degrading system.

The simple and complex cases of degradation were studied for Type I and Type II ladder polymers. The percent vaporization at time kt and the rate of weight loss at time kt were calculated and compared with a single chain polymer degrading under identical conditions. The constant, k, is the proportionality constant between the rate of breaking bonds and the number of unbroken bonds in the degrading system. It can only be determined experimentally, so the time factor is kt instead of t, where t is time.

MONTE CARLO MODEL

To construct a Monte Carlo (Reference 2) model for the degradation reaction, a portion of the computer storage is set aside to represent the polymer molecules. Each storage location represents one bond. If a bond is not broken, a zero is placed in the computer storage location corresponding to that bond.




Figure 1. Ladder Polymer Model

In the simple case, when a bond is broken it is set equal to 1 and the opposite bond checked. If the opposite bond is broken, both bonds are set equal to 2. In the complex case, when an isolated bond is broken (bond 3 in Figure 1), it is set equal to 1. If vaporization occurs through the breaking of adjacent side chain bonds only (bonds 1, 10, 11, and 3 in Figure 1 are broken), the side chain bonds are set equal to 2. Since x broken side chain bonds result in x-1 atoms vaporizing, all of the broken side chain bonds are set equal to 2 except the last one so that each bond which is set egual to 2 corresponds to a vaporized atom. If two opposite bonds are broken (bond 2 and 6 are broken in Figure 1), they are set equal to 3 except when a bond is broken opposite a bond which has a number 2 in its storage location. The initial broken bond is set equal to 3, but the opposite bond is changed from a 2 to a 5. If two pairs of opposite broken bonds result in vaporization (bonds 1 and 5 and bonds 4 and 8 in Figure 1 are broken), all of the bonds in the vaporized fragment are set equal to 4. If any of the bonds have numbers 2 or 5 in their storage, they are also set equal to 4, but the number of vaporized atoms is reduced by one. This prevents the same atom from being vaporized twice. If bonds 1, 5, 10, and 6 in Figure 1 are broken and the computer then breaks bond 2, an error will result because only one atom must be vaporized and not two. If the bond opposite the initial broken bond has a number of 3, 4, or 5, the computer checks whether its adjacent bond also has a number of 3, 4, or 5 and if it does, no vaporization of that atom occurs (it has been vaporized previously). If the opposite bond has a number 2 in it, it is set equal to 5 and no vaporization is recorded as described previously.

Initially, all of the storage locations are set to zero. A random number is generated which has the limits of 0 to B -1, where B is the total number of bonds initially present in the system. Each number then represents a particular bond in a particular molecule and the number of molecules and the number of bonds per molecule are selected by the programmer and can readilybe altered. The present study investigated a system of 100 molecules with 199 bonds per molecule for ladder polymer Type 1 and 100 molecules with 196 bonds per molecule for ladder polymer Type II. A single chain polymer with the same number of bonds per molecule was degraded in the computer for comparison purposes.

When a random number is generated, the bond which it represents is checked to see whether or not it is broken. If it is already broken, a duplicate is recorded and a new random number generated. If it is not broken. the bond is set equal to one and the opposite bond checked. If the opposite bond is broken, in the simple case both bonds are set equal to 2. The computer then checks the adjacent bonds in both directions until it comes to another pair of opposite bonds with a value of 2 or the end of the molecule. The size of the fragment is measured and if it contains ten atoms or less, vaporization occurs. All of the vaporized bonds are set equal to 2 and the concentration of unbroken bonds is adjusted to account for the vaporized bonds. The size of the fragments which are volatile is arbitrary and can be varied if desired.

In the complex case, if the opposite bond is broken, both bonds are set equal to 3 except when the opposite bond has a value of 2. The opposite bond is then set equal to 5 and the original broken bond is set equal to 3. The computer then checks the side chain bonds in both directions until it comes to another pair of opposite bonds with a value of 3, 4, or 5 or until it comes to the end of the molecule. The size of the fragment is measured and if it contains ten atoms or less, vaporization occurs. Before the vaporized bonds are set equal to 4, they are checked to see if their value is 0, 2, or 5. The total number of atoms in the fragment minus the number of bonds containing 2 or 5 equals the number of atoms vaporized. The number of bonds which are changed from 0 to 4 is also calculated and the number of unbroken bonds left in the system is reduced by that number of bonds.

If no vaporization occurs or if the opposite bond is not broken, no further work is done in the simple case and a new random number is generated. If the opposite bond is broken and no vaporization occurs in the complex case, the crosslinks are checked to see if broken crosslinks can lead to a broken molecule. The computer checks all of the crosslinks to the left and right until it either comes to an unbroken crosslink or the last crosslink at the end of the molecule. If the computer finds an unbroken crosslink, it then scans all of the side chain bonds on both sides of the ladder polymer from the broken bond produced by the random number generator to the last side chain bond before the unbroken crosslink. If a broken bond is found on the side of the molecule opposite the original broken bond, the computer treats it exactly as described previously for the case of two opposite bonds breaking. If a broken bond is found on the side of the molecule adjacent to the original broken bond or if all of the crosslinks to the end of the molecule are broken, the computer checks to see if the fragment contains ten or less atoms. If it does, all of the bonds are set equal to 2 and the total number of unbroken bonds remaining in the system is reduced by the number of bonds changed from 0 to 2. If the opposite bond is not broken in the complex case, the computer scans the crosslinks and does all of the calculations previously described.

If the random number generator produces a bond which corresponds to a crosslink, no further work is done in the simple case. In the complex case, the computer checks to see if the broken crosslink will result in a broken molecule. If it does, it then checks to see if the fragments are small enough to be vaporized and adjusts the bond numbers accordingly.

The time factor kt is equal to $\ln (B_0/B)$ where B_0 is the number of bonds present initially and B is the number of unbroken bonds present at time kt. The number of unbroken bonds present at time kt equals the number of bonds present initially minus the number of random numbers generated plus the number of duplicates recorded minus the number of unbroken bonds vaporized out of the system. The computer calculates the number of atoms vaporized out of the system, the percent vaporization, and the rate of vaporization at time kt and prints out the desired data at convenient intervals of kt.

RESULTS

The curves shown for the simple case in Figure 2 and the complex case in Figure 3 are based on computer calculations for the percent vaporization versus kt. As the degrading single chain polymer undergoes a much more rapid decrease in molecular weight when compared to a ladder polymer (Reference 1), we would naturally predict that the single chain polymer would also lose weight at a much faster rate. Examination of Figures 2 and 3 shows quite clearly that this prediction is correct. When 10 percent of the single chain polymer has vaporized, less than 2 percent of the ladder polymer has vaporized in the simple case and less than 4 percent in the complex case. A difference in the shapes of the

curves is also readily apparent. The single chain polymer shows a large initial loss in weight during degradation while the ladder polymers have an induction period during which the loss in weight is very small. As degradation proceeds, the shapes of the curves become identical and merge together. The curves for the rate of weight loss versus kt are shown in Figure 4 for the single case and in Figure 5 for the complex case. The very large initial rate of weight loss for a single chain polymer as compared to a ladder polymer is the major point of interest of these curves. These results indicate that the ladder polymers should have increased thermal stability over single chain polymers.

REFERENCES

- 1. M. M. Tessler, Technical Documentary Report No. ML-TDR-64-151, July 1964. Research and Technology Division, Wright-Patterson Air Force Base, Ohio.
- 2. A. S. Householder, G. E. Forsythe, and H. H. Germand, Monte Carlo Method, National Bureau of Standards, Applied Mathematics Series, 12 (1951).




Figure 2. Plot of Percent Vaporization Versus Time for Simple Case Ladder Polymers Undergoing Random Degradation.






Figure 3. Plot of Percent Vaporization Versus Time for Complex Case Ladder Polymers Undergoing Random Degradation.



Plot of Rate of Weight Loss Versus Time for Simple Case Ladder Polymers Undergoing Random Degradation, Figure 4.



Plot of Rate of Weight Loss Versus Time for Complex Case Ladder Polymers Undergoing Random Degradation. Figure 5.

APPENDIX I

COMPUTER PROGRAM

VAPORIZATION OF SINGLE CHAIN POLYMER

```
FREQUENCY 7(5,1,0),110(9,1,1),194(5,1,0),118(1,1,9),196(5,1,0)
C10 VOLATIZATION OF SINGLE CHAIN FROM RANDOM NUMBER GENERATION
                                                                                                                                                                                                   LESS
                                                                                                                                                                                                  C VAPORIZATION OCCURS WHEN CHAIN IS TEN ATOMS OR
                                                                                                                                                                                                                                                                                                                                                                                                                                                       REMOVED FROM SYSTEM
                                                1,151(0,1,9),200(0,1,1),204(0,1,1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              IF(1-L(ML,NBAKK))126,126,205
                                                                                                                                                                                                                                                                                                                                                                                                        IF(1-L(ML,NBAKK))125,125,201
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             IF(L(ML,NBAKW)-1)115,108,108
                                                                                                                                                                                                                                                                       IF(L(ML,NBAKW)-1)103,105,105
                                                                                                                                                                                                                                                                                                        CHECKED ALL BREAKS TO THE RIGHT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           CHECKED ALL BREAKS TO THE LEFT
                  DIMENSION L(100,200), E(10)
                                                                                                                                                                                                                                      IF(NB+KW-199)104,104,105
                                                                                                                                                                     IF(L(ML,NB)-1)28,11,11
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           IF (NB-KW) 108,108,116
                                                                                                      R=RAND1 (Y) *19900.
                                                                                                                                                                                                                                                                                                                                                                                                                                                         C VAPORIZED SEGMENTS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                           DO 115 KW=1,10
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                E(KB)=E(KB)+1.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               DO 126 KK=1,KW
                                                                                                                                                                                                                       DO 103 KW=1,10
                                                                                                                                                                                                                                                                                                                                                          E(KB) = E(KB) + 1.
                                                                                                                                                                                                                                                                                                                                                                           DO 125 KK=1,KW
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 L (ML,NBAKK)=1
                                                                                                                                                                                                                                                                                                                                                                                                                                          L(ML,NBAKK)=1
                                                                    DO 25 IX=1,70
                                                                                    DO 24 I=1,200
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                BVOL=BVOL+1'.
                                                                                                                                                                                                                                                                                                                                                                                                                            BVOL=BVOL+1.
                                                                                                                                                      NB=199*ML-NR
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              NBAKW=NB-KW
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 NBAKK = NB - KK
                                                                                                                                                                                                                                                         NBAKW=NB+KW
                                                                                                                                                                                                                                                                                                                                                                                           NBAKK=NB+KK
                                                                                                                                       ML=NR/199+1
                                                                                                                                                                                       L(ML,NB)=1
                                                                                                                                                                                                                                                                                                                         GO TO 150
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              GO TO 24
                                                                                                                                                                                                                                                                                        CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               KB=KW
                                                                                                                                                                                                                                                                                                                                          KB=KW
                                                                                                                      NR=R
                                                                                                                                                                                                                                                                                          103
                                                                                                                                                                                                                                                                                                                                                                                                                                                                            150
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             116
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              115
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              961
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               205
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             118
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 108
                                                                                                                                                                                                                                                         104
                                                                                                                                                                                                                                                                          194
                                                                                                                                                                                                                                                                                                                                            105
                                                                                                                                                                                                                                                                                                                                                                                                                             201
                                                                                                                                                                                                                                                                                                                                                                                                                                           125
```

C VAPORIZED SEGMENTS REMOVED FROM SYSTEM

```
07059U00
                                                                                                                                                                                                                                                                                                                                                                                       -07050001
                                                                                                                                                                                                                                                                                                                                                                                                      07059U02
                                                                                                                                                                                                                                                                                                                                                                                           4
                                                                                                                                                                                                                                                                                                                                                                                        4E
                                                                                                             VOL=E(1)*14.+E(2)*28.+E(3)*42.+E(4)*56.+E(5)*70.+E(6)*84.
                                                                                                                                                                                                                                                                                                                                                                                       5
                                                                                                                                                                                                                                                                                                                                                                                       5
                                                                                                                                                                                                                                                                                      WRITE OUTPUT TAPE 3,30,PCVOL,TIME,DWT,NDUP,VOL
                                                                             TIME=LOGF(19900./(19900.-200.*XI+DUPN-BVOL))
                                                                                                                                                                                                                                                                                                                                                                                       78
                                                                                                                                                                                                                                                                                                                                                                                                      σ
                                                                                                                            1 +E(7)*98•+E(8)*112•+E(9)*126•+E(10)*140•
                                                                                                                                                                                                                                                                                                                                                                                       94
                                                                                                                                                                                                                                                                                                                                                                                       95
                                                                                             C MOLECULAR WEIGHT OF EACH ATOM IS 14
                                                                                                                                                                                                                                                                                                                                                                                       6
                                                                                                                                                                                                                                        \mathsf{DWT} = (\mathsf{A}(\mathsf{IX}) - \mathsf{A}(\mathsf{IY})) / (\mathsf{T}(\mathsf{IX}) - \mathsf{T}(\mathsf{IY}))
                                                                                                                                           PCVOL=100.*VOL/(200.*1400.)
                                                                                                                                                                                                                                                                                                      FORMAT(1X,3F20.6,115,F20.2)
                                                                                                                                                          DIMENSION A(70),T(70)
                                                                                                                                                                                                          IF(IX-1)152,152,155
                                                                                                                                                                                                                                                                                                                                                                                                  5484
                                                                                                                                                                                                                                                                        DWT = A(IX)/T(IX)
                                                                                                                                                                                                                                                                                                                                                                                     W
I
             NDUP=NDUP+1
                                                                                                                                                                                           T(IX)=TIME
                                                               DUPN=NDUP
                                                                                                                                                                                                                                                         GO TO 153
                                                                                                                                                                            A(IX)=VOL
                                                                                                                                                                                                                                                                                                                                      CALL EXIT
GO TO 24
                                                                                                                                                                                                                                                                                                                       CONTINUE
                              CONTINUE
                                                                                                                                                                                                                         IY = IX - 1
                                                  XI = IX
                                                                                                                                                                                                                                                                                                                                                                                  *J -9(NZ5GA
                                                                                                                                                                                                                                                                                                                                                     END
                                                                                                                                                                                                                                                                                                                                                                                                 *U7(P(ST
                                                                                                                                                                                                                       155
                                                                                                                                                                                                                                                                        152
                                                                                                                                                                                                                                                                                    153
                             24
                                                                                                                                                                                                                                                                                                      30
                II
```

APPENDIX II

COMPUTER PROGRAM

VAPORIZATION OF LADDER POLYMER

SIMPLE CASE - TYPE I

```
5,233(1,1,3),236(1,1,3),320(0,1,9),330(0,1,9),360(0,1,9),390(0,1,9
                                                                                                                                                                    6,500(1,1,5),310(1,1,5),600(1,1,5),340(1,1,5),610(1,1,5),370(1,1,5
                                                          1,118(1,1,9),196(5,1,0),4(1,0,1),10(5,1,1),13(1,1,5),133(9,1,1)
                                       FREQUENCY 7(1,0,2),8(5,1,1),9(5,1,1),110(9,1,1),194(5,1,0)
                                                                                                                           4,216(1,1,3),220(1,1,3),223(1,1,3),226(1,1,3),230(1,1,3)
                                                                                                     3,200(1,1,3),203(1,1,3),206(1,1,3),210(1,1,3),213(1,1,3)
                                                                                  2,184(5,1,0),140(1,1,9),192(5,1,0),14(5,1,1),150(0,1,9)
LESS LADDER UNITS VOLATILE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         IF(L(ML,NBAKW)-2)103,105,105
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        [F(1-L(ML,NBAKK))201,201,202
                                                                                                                                                                                                                                                                                                                                                                                                        IF (L(ML,NB+66)-1)24,100,100
  80
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    RIGHT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         [F(1-L(ML,NN))204,204,205
                     DIMENSION L(100,200),E(6)
  FOUR
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              IF (NB+KW-66)104,104,105
                                                                                                                                                                                                                                                                                                                                                               IF(L(ML,NB)-1)28,11,11
                                                                                                                                                                                           7,620(1,1,5),400(1,1,5)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                C CHECKED ALL BREAKS TO THE
 POLYMER
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          F(KW)310,310,300
                                                                                                                                                                                                                                                       R=RAND1 (Y) *19900.
                                                                                                                                                                                                               DO 25 IX=1, 40
                                                                                                                                                                                                                                                                                                                                          IF(NB-66)8,8,4
                                                                                                                                                                                                                                                                                                                                                                                                                                                                       C MOLECULE IS BROKEN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                DO 125 KK=1+KW
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 E(KB) = E(KB) + 1
                                                                                                                                                                                                                                   DO 24 I=1,800
                                                                                                                                                                                                                                                                                                                                                                                                                                                   L(ML,NB+66)=2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            DO 103 KW=1+5
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               L(ML,NBAKK)=2
                                                                                                                                                                                                                                                                                                                      NB=199*ML-NR
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     NBAKW=NB+KW
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   NBAKK=NB+KK
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              BVOL=BVOL+1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      NN=NB+66+KK
                                                                                                                                                                                                                                                                                                 ML=NR/199+1
                                                                                                                                                                                                                                                                                                                                                                                   L(ML,NB)=1
                                                                                                                                                                                                                                                                                                                                                                                                                              L(ML,NB)=2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       GO TO 114
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      KW=KB-1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            KB=KW
                                                                                                                                                                                                                                                                            NR=R
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              103
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     104
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          194
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             105
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          320
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              300
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           202
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         203
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             205
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                201
```

```
C VAPORIZED SEGMENTS REMOVED FROM SYSTEM
                                                                                                             IF (1-L (ML,NB+133))503,503,504
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            F(1-L(ML,NB+132))507,507,508
                                                                                                                                                                                                               IF(L(ML,NBAKW)-2)115,108,108
                                                                                                                                                                                                                                                                                                                                                         F(1-L(ML,NBAKK))211,211,212
                                                                   IF (1-L(ML,NY+1))501,501,502
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   F(1-L(ML,NY-1))505,505,506
                                                                                                                                                                                                                                          CHECKED ALL BREAKS TO THE LEFI
                                                                                                                                                                                                                                                                                                                                                                                                                  F(1-L(ML,NN))214,214,215
                         IF(1-L(ML,NY))125,125,207
                                                                                                                                                                                                                                                                                                                                                                                                                                                                         F(1-L(ML,NY))131,131,217
                                                                                                                                                                                 IF(NB-KW)108,108,116
                                                                                                                                                                                                                                                                                                                IF (KW)340,340,350
                                                                                                                                         L(ML,NB+133)=2
                                                                                                                                                                                                                                                                                                                             DO 131 KK=1,KW
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         (ML • NB+132)=2
                                                                                                                                                                                                                                                                                    E(KB)=E(KB)+1.
                                                                                                                                                                      DO 115 KW=1,5
                                                                                                                                                                                                                                                                                                                                                                                     - (ML , NBAKK) =2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          BVOL=BVOL+1.
                                          BVOL=BVOL+1.
                                                                                  BVOL=BVOL+1.
                                                                                                                            BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       3V0L=BV0L+1.
              NY=NB+132+KK
                                                                                               L (ML, NY+1)=2
                                                                                                                                                                                                                                                                                                                                                                         BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                                                                                                BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                                                                                                                          NY=NB+133-KK
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               . (ML ,NY-1)=2
                                                                                                                                                                                                 NBAKW=NB-KW
                                                                                                                                                                                                                                                                                                                                             NBAKK=NB-KK
                                                                                                                                                                                                                                                                                                                                                                                                    NN=NB+66-KK
                                                        (ML_9NY)=2
                                                                                                                                                                                                                                                                                                                                                                                                                                             . (ML, NN)=2
L (ML, NN)=2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     _ (ML,NY)=2
                                                                                                                                                                                                                            CONTINUE
                                                                                                                                                                                                                                                         60 TO 24
                                                                                                                                                                                                                                                                                                   KW=KB-1
                                                                                                                                                                                                                                                                      KB=KW
                                                                                                                                                                                                 116
196
 204
                                                                                                                                                                                                                                                                       108
                                                                                                                                                                                                                                                                                                                 330
                                                                                                                                                                                                                                                                                                                             350
                                                                                  502
                                                                                                                             504
                                                                                                                                                                                                                                                                                                                                                           210
212
                                                                                                 501
                                                                                                                                                                                                                                                                                                                                                                                     211
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    600
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 506
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       217
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      131
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              505
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             340
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           508
```

```
C VAPORIZED SEGMENTS REMOVED FROM SYSTEM
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               REMOVED FROM SYSTEM
                                                                                                                                                                   IF(L(ML,NBAKW)-2)132,135,135
                                                                                                                                                                                                                                                                                                               IF(1-L(ML,NBAKK))221,221,222
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    [F(1-L(ML *NB+67))511,511,512
                                                                     IF(1-L(ML,NB-66))120,120,24
                                                                                                                                                                                                                                                                                                                                                                                                                                                                          [F(1-L(ML.NY+1))509,509,510
                                                                                                                                                                                               C CHECKED ALL BREAKS TO THE RIGHT
                                                                                                                                                                                                                                                                                                                                                                       IF (1-L(ML,NN))224,224,225
                                                                                                                                                                                                                                                                                                                                                                                                                                IF(1-L(ML,NY))136,136,227
                                                                                                                                        IF (NB+KW-132)134,134,135
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          IF (NB-KW-66)148,148,142
                                          IF(L(ML,NB)-1)17,11,11
                          IF (NB-132)10,10,14
                                                                                                                                                                                                                                                                    IF (KW) 370,370,380
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            C VAPORIZED SEGMENTS
                                                                                               C MOLECULE IS BROKEN
                                                                                                                                                                                                                                                                                  DO 136 KK=1,KW
                                                                                                                                                                                                                                         E(KB)=E(KB)+1.
                                                                                                                         DO 132 KW=1,5
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                L (ML , NB+67)=2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           DO 139 KW=1,5
                                                                                                                                                                                                                                                                                                                                            (ML NBAKK)=2
                                                                                                                                                                                                                                                                                                                             3VOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                                                      3VOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                                                                                                             BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      - (ML ,NY+1)=2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  BVOL=BVOL+1.
                                                                                                                                                     NBAKW=NB+KW
                                                                                                                                                                                                                                                                                                                                                         NN=NB-66+KK
                                                                                                                                                                                                                                                                                                 NBAKK=NB+KK
                                                                                                                                                                                                                                                                                                                                                                                                                 NY=NB+66+KK
                                                       L(ML_NB)=1
                                                                                                                                                                                                                                                                                                                                                                                                    - (ML, NN)=2
                                                                                                                                                                                                                                                                                                                                                                                                                                                            _ (ML,NY)=2
                                                                                    L (ML, NB)=2
                                                                                                                                                                                                             60 TO 138
                                                                                                                                                                                 CONTINUE
                                                                                                                                                                                                                                                        KW = KB - 1
                                                                                                                                                                                                                            KB=KW
                                                                                                                                                                                 132
                                                                                                                                        133
                                                                                                                                                      134
                                                                                                                                                                   184
                                                                                    120
                                                                                                                                                                                                                            135
                                                                                                                                                                                                                                                                       360
                                                                                                                                                                                                                                                                                  380
                                                                                                                                                                                                                                                                                                                            222
                                                                                                                                                                                                                                                                                                                                                                                     225
                                                                                                                                                                                                                                                                                                                                                                                                                                                            136
                                                                                                                                                                                                                                                                                                                                                                                                                                                                          610
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       510
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     509
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          140
                                                                                                                                                                                                                                                                                                                                          221
                                                                                                                                                                                                                                                                                                                                                                                                                                             227
```

```
VOL=E(1)*28.+E(2)*56.+E(3)*84.+E(4)*112.+E(5)*140.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          TIME=LOGF(19900./(19900.-800.*XI+DUPN-BVOL))
                                                                                                                                                                                                                                                                                                                                                                                                          REMOVED FROM SYSTEM
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         C MOLECULAR WEIGHT OF EACH ATOM IS 14
             F(L(ML,NBAKW)-2)139,148,148
                                                                                                                                                                                                                                                                                                                                                                 IF (1-L (ML,NB+66))515,515,516
                                                                                                                                                          IF (1-L(ML, NBAKK))231,231,232
                                                                                                                                                                                                                                                                                                                       IF(1-L(ML,NY-1))513,513,514
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    PCVOL=100.*VOL/(134.*1400.)
                                       C CHECKED ALL, BREAKS TO THE LEFT
                                                                                                                                                                                                                IF(1-L(ML,NN))234,234,235
                                                                                                                                                                                                                                                                           IF(1-L(ML,NY))149,149,237
                                                                                                                                                                                                                                                                                                                                                                                                                                       IF(L(ML,NB)-1)12,11,11
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    DIMENSION A(70) T(70)
                                                                                                              IF (KW) 400,400,410
                                                                                                                                                                                                                                                                                                                                                                                                         C VAPORIZED SEGMENTS
                                                                                                                             DO 149 KK=1,KW
                                                                                   E(KB)=E(KB)+1.
                                                                                                                                                                                      (ML,NBAKK)=2
                                                                                                                                                                                                                                                                                                                                                                                              _ (ML,NB+66)=2
                                                                                                                                                                        BVOL=BVOL+1.
                                                                                                                                                                                                                                 BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                         BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                    BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                                               BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                  L(ML_NY-1)=2
                                                                                                                                           NBAKK=NB-KK
                                                                                                                                                                                                   NN=NB-66-KK
NBAKW=NB-KW
                                                                                                                                                                                                                                                            NY=NB+67-KK
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  NDUP=NDUP+1
                                                                                                                                                                                                                                                                                                       L(ML,NY)=2
                                                                                                                                                                                                                                              L (ML, NN)=2
                                                                                                                                                                                                                                                                                                                                                                                                                                                     L(ML_NB)=1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            DUPN=NDUP
                           CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                        GO TO 24
                                                                                                                                                                                                                                                                                                                                                                                                                                                                    42 CI 09
                                                       GO TO 24
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                CONTINUE
                                                                                                 KW=KB-1
                                                                    KB=KW
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               XI = IX
                           139
                                                                      148
                                                                                                                 390
                                                                                                                              410
                                                                                                                                                           230
                                                                                                                                                                                                                  233
                                                                                                                                                                                                                                 235
                                                                                                                                                                                                                                              234
                                                                                                                                                                                                                                                                            236
                                                                                                                                                                                                                                                                                        237
                                                                                                                                                                                                                                                                                                        149
                                                                                                                                                                                                                                                                                                                       620
                                                                                                                                                                                                                                                                                                                                    514
                                                                                                                                                                                                                                                                                                                                                 513
                                                                                                                                                                                                                                                                                                                                                                 400
              192
                                                                                                                                                                                      231
                                                                                                                                                                                                                                                                                                                                                                               516
                                                                                                                                                                                                                                                                                                                                                                                                                                         14
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                24
                                                                                                                                                                                                                                                                                                                                                                                                                                                    12
```

```
070SQU00
-070SQU01
070SQU02
                                                                                                                             -5 -5 -7
                                                       DWT=A(IX)/T(IX)
WRITE OUTPUT TAPE 3,30,PCVOL,TIME,DWT,NDUP,VOL
                                                                                                                              46
                                                                                                                                        2(X)
                                                                                                                               95
                                                                                                                               6
                                     DWT=(A(IX)-A(IY))/(T(IX)-T(IY))
GO TO 153
                                                                            FORMAT(IX,3F20.6,115,F20.2)
CONTINUE
CALL EXIT
                  IF(IX-1)152,152,155
IY=IX-1
                                                                                                                                          5484
          T(IX)=TIME
A(IX)=VOL
                                                                                                                      )1 (X- - (
*J -9(NZ5GA 7
*U7(P($T
                                                                                                             END
                                                            152
153
                     150
155
                                                                                30
```

APPENDIX III COMPUTER PROGRAM VAPORIZATION OF LADDER POLYMER SIMPLE CASE - TYPE II

```
,723(1,1,5),731(1,1,5),118(1,1,9),122(5,1,0),330(0,1,9),813(1,1,5)
                                                                                                                                                                                                                                   ',348(1,1,5),350(1,1,0),351(0,1,5),352(0,1,5),361(9,1,1),365(5,1,0)
                                                                                                                                                                                                                                                              8,371(0,1,9),374(1,1,5),381(1,1,5),384(9,1,1),387(5,1,0),391(0,1,9)
                                                                              !,702(1,1,0),703(0,1,5),704(0,1,5),711(9,1,1),714(5,1,0),716(0,1,9
                                                                                                                                          4,742(1,1,0),743(0,1,5),744(0,1,5),751(1,1,9),757(5,1,0),758(0,1,9)
                                                                                                                                                                                                     6,404(1,1,5),402(1,1,5),412(1,1,5),340(9,1,1),343(5,1,0),344(0,1,9
                                                                                                                                                                                                                                                                                           9,394(1,1,5),600(1,1,0),601(0,1,5),602(0,1,5),611(1,1,9),614(5,1,0
                                                                                                                                                                                                                                                                                                                                                                                     2,910(1,1,5),900(1,1,0),940(0,1,5),941(0,1,5),947(0,1,1),980(0,1,1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      C LOP=0 MEANS ADJACENT BOND NOT BROKEN//IF LOP=1, ADJACENT BOND BROKEN
                                                      •41(1•1•5)•43(1•1•5)•110(9•1•1)•194(9•1•0)•320(0•1•9)•200(1•1•5
                                                                                                                                                                         5,762(1,1,5),770(1,1,5),4(1,0,1),10(0,1,1),400(1,1,0),401(1,1,5)
                                                                                                                                                                                                                                                                                                                           FREQUENCY 630(0,1,9),634(1,1,5),661(1,1,5),14(5,1,1),690(0,1,9)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      EVEN NUMBER
                          FREQUENCY 7(1,0,2),8(0,1,1),700(1,1,0),40(1,1,5),42(1,1,5)
                                                                                                                                                                                                                                                                                                                                                                                                                   3,948(0,1,1),951(0,1,1),981(0,1,1),952(0,1,1),960(3,0,1)
LADDER UNITS VOLATILE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  LOPP=0 MEANS NB IS ODD NUMBER///LOOP=1 MEANS NB IS
                                                                                                                                                                                                                                                                                                                                                         1,260(0,1,5),270(0,1,5),281(0,1,5),290(0,1,5)
   C14 TYPE II LADDER POLYMER TWO OR LESS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       IF(2-L(ML,NB-1))944,945,944
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  IF(2-L(ML,NB+1))942,943,942
                                                                                                                                                                                                                                                                                                                                                                                                                                                   DIMENSION L(100,200),E(6)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            IF(1-L(ML,NB))11,11,911
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      IF(2*NA-NB)940,941,940
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              IF (NB-156)910,910,14
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            R=RAND1(Y)*19600
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 DO 25 IX=1,60
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              DO 24 I=1,800
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  NB=196*ML-NR
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             E(1) = E(1) + 1 \bullet
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      ML=NR/196+1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    L(ML,NB)=2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          NA=NB/2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        GO TO 7
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               LOPP=0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            LOPP=0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     _0PP=1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             GO TO
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               GO TO
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               LOPP=1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   0=d0-
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  LOP=0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   L0P=1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       943
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               945
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            910
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      911
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        006
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      940
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                945
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           941
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     446
```

```
C CHECKED ALL BREAKS TO THE RIGHT ON TOP
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 IF(2-L(ML,NB+78))708,709,708
                                                                                                                                                                                                                                                                                                                                                                 IF(L(ML,NBAKW)-2)103,800,800
                                                                                                                                                                                                                                                                                                                                                                                                                                                              IF(2-L(ML,NB+78))707,705,707
                                                                                                                                                                                                                              IF(1-L(ML;NB+78))102;102;43
                                                                                                                                  IF(1-L(ML,NB+78))100,100,42
                                                                                                                                               IF(1-L(ML,NB+79))101,101,24
                                                                                                                                                                                                                                            IF(1-L(ML,NB+77))203,203,24
                                                                                                                                                                                                                                                                                                                                        IF (NB+KW-78)106,106,800
                                                                                                                                                                                                                                                                                                                                                                                                                                                 IF (2*NA-NB) 703, 704, 703
                                                   IF(NB-78)8,8,4
IF(1-LOP)947,947,28
                                                                                                                    IF(2*NA-NB)40,41,40
                                                                             IF (LOPP)114,114,701
                                                                                                                                                                                                                                                                                                              MOLECULE IS BROKEN
                                                                                                                                                                                                                                                                                                                          DO 103 'KW=1,5
                                                                                                                                                                                                                                                                                   L(ML,NB+78)=2
                                                                                                                                                           L(ML,NB+79)=2
                                                                                                                                                                                      L(ML,NB+78)=2
                                                                                                                                                                                                                                                         L (ML, NB+77)=2
                           E(1) = E(1) + 1 \bullet
                                                                                                                                                                                                                                                                                                                                                    NBAKW=NB+KW
             L(ML,NB)=2
                                                                                                                                                                                                                                                                                                  L(ML,NB)=2
                                                                                                                                                                                                    L(ML,NB)=2
                                                                                           L(ML,NB)=1
                                                                                                                                                                         GO TO 105
                                                                                                                                                                                                                                                                      GO TO 104
                                                                                                                                                                                                                                                                                                                                                                                                          GO TO 980
                                                                                                                                                                                                                 GO TO 701
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         GO TO 706
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    GO TO 706
                                                                                                                                                                                                                                                                                                                                                                                                                                                                           NBA=NB+79
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    NBA=NB+78
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             NBA=NB+77
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          GO TO 706
                                                                                                                                                                                                                                                                                                                                                                               CONTINUE
                                                                                                        NA=NB/2
                                                                                                                                                                                                                                                                                                                                                                                                                        NA=NB/2
                                                                                                                                                                                                                                                                                                                                                                                                                                     NKW=KW
L0P=1
                                                                                                                                                                                                                                                          203
                                                                                                                                                                                                                                                                                                                                                                                                                        800
                                                                                                                                                                                                                                                                                                                                                                                                                                                  702,
703,
707
                                                                                                                      700
40
                                                                                                                                              42
                                                                                                                                                                                        100
                                                                                                                                                                                                                                            43
                                                                                                                                                                                                                                                                                     102
                                                                                                                                                           101
                                                                                                                                                                                                    105
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      705
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 704
708
                                                                                                                                                                                                                                                                                                                            701
                                                                                                                                                                                                                                                                                                                                                                   194
                                                                             246
```

```
C CHECKED ALL BREAKS TO THE RIGHT ON BOTTOM 715 E(KV) = E(KV) + 1.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  C VAPORIZED SEGMENTS REMOVED FROM SYSTEM
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 IF(L(ML,NBAKW)-2)115,810,810
                                                                                                                                                                                                                                                                                                                                                                                                                                         IF (1-L(ML,NBAKK))730,730,733
                                                   [F(L(ML,NBAKV)-2)710,715,715
                                                                                                                                                                                        IF (1-L(ML, NBAKK))722,722,725
                                                                                                                                                                                                                                                                                                                  IF (1-L(ML,NBAKK))125,125,202
                                                                                                                                                                                                                                                                                                                                                                      NX=NBAKV-78-(NBAKV-78)/2+157
                         [F(N8A+KV-156)712,712,715
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       [F(NB-KW)810,810,121
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                IF(LOP)114,114,948
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              F(LOPP)114,114,24
                                                                                                                                                                                                                                                                        IF (KW)310,310,300
                                                                                                                                                                                                                                                                                                                                                                                                 IF(KB)980,980,251
                                                                                                                                               F(KV)108,108,721
                                                                                                                                                                                                                                                                                                                                                                                                                DO 730 KK=1,KB
                                                                                                                                                                                                                                                                                       DO 125 KK=1,KW
                                                                                                                                                              DO 722 KK=1,KV
                                                                                                                                                                                                                                                                                                                                                          NW=NB-NB/2+157
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           DO 115 KW=1,5
                                                                                                                                                                                                                                                                                                                                                                                                                                                                      L (ML NBAKK)=2
                                                                                                                                                                                                                                                                                                                                                                                                                             NBAKK=NW-1+KK
             DO 710 KV=1,5
                                                                                                                                                                                                                                                                                                                                            L(ML,NBAKK)=2
                                                                                                                                                                                                                    .(ML,NBAKK)=2
                                                                                                                                                                                                                                              E(KW) = E(KW) + 1
                                       NBAKV=NBA+KV
                                                                                                                                                                                                                                                                                                                                                                                                                                                        BVOL=BVOL+1.
                                                                                                                      NBAKV=NBA+KV
                                                                                                                                                                            NBAKK=NBA+KK
                                                                                                                                                                                                       BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                               BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     NBAKW=NB-KW
                                                                                                                                                                                                                                                                                                     NBAKK=NB+KK
                                                                               GO TO 980
NBA=NB+78
                                                                                                                                                                                                                                                                                                                                                                                     KB=NX-NW
                                                                  CONTINUE
                                                                                                                                   KV=KV-1
                                                                                                                                                                                                                                                            KW=KW-1
                                                                                                                                                                                                                                 KW=NKW
                                                                                                                                                                                                                                                                                                                                                                                                                                                        733
                                                                                                                                                                                                                                                                         320
                                                                                                                                                                                                                                                                                      300
                                                                                                                                                                                                     725
                                                                                                                                                                                                                                                                                                                                            125
                                                                                                                                                                                                                                                                                                                                                          310
                                                                                                                                                                                          723
                                                                                                                                                                                                                                108
                                                                                                                                                                                                                                                                                                                               202
                                                                                                                                                                                                                                                                                                                                                                                                                                          731
                                                                                                                                                                                                                    722
                                                                                                                                                                                                                                                                                                                  200
                                                                                                                                                                                                                                                                                                                                                                                                                                                                      730
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              980
                                                                                                                                                716
                                                                                                                                                                                                                                                                                                                                                                                                    260
251
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              948
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           114
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       118
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     121
122
                                        712714
```

```
TO THE LEFT ON BOTTOM
            ON TOP
                                                                                                                                                                                                                                IF(L(ML, NBAKV)-2)750,755,755
                                                                                                                                         IF(2-L(ML,NB+78))748,749,748
                                                                                                                                                                                                                                                                                                                                                             IF(1-L(ML,NBAKK))781,781,764
                                                                                                                                                                                                                                                                                                                                                                                                                                                                              IF(1-L(ML,NBAKK))812,812,814
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               NX=NBAKV-78-(NBAKV-78)/2+157
                                                                          IF(2-L(ML,NB+78))747,745,747
                                                                                                                                                                                                       IF (NBA-KV-79) 755,756,756
            CHECKED ALL BREAKS TO LEFT
                                                             IF(2*NA-NB)743,744,743
                                                                                                                                                                                                                                                                                                                       IF(KV)120,120,761
                                                                                                                                                                                                                                                                                                                                                                                                                                        IF(KW)760,760,811
                                                                                                                                                                                                                                                                     C CHECKED ALL BREAKS
                                                                                                                                                                                                                                                                                                                                                                                                                                                     DO 812 KK=1,KW
                                                                                                                                                                                                                                                                                                                                    DO 781 KK=1,KV
                                                                                                                                                                                                                                                                                 E(KV) = E(KV) + 1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   NW=NB-NB/2+157
                                                                                                                                                                                                                                                                                                                                                                                                               E(KW)=E(KW)+1.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       L(ML,NBAKK)=2
                                                                                                                                                                                           DO 750 KV=1,5
                                                                                                                                                                                                                                                                                                                                                                                      L(ML,NBAKK)=2
                                                                                                                                                                                                                    NBAKV=NBA-KV
                                                                                                                                                                                                                                                                                               NBAKV=NBA-KV
                                                                                                                                                                                                                                                                                                                                                 NBAKK=NBA-KK
                                                                                                                                                                                                                                                                                                                                                                         BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                 NBAKK=NB-KK
                                                                                        NBA=NB+79
                                                                                                                              GO TO 746
                                                                                                                                                                  GO TO 746
                                                                                                                                                                               NBA=NB+78
                                                                                                    60 TO 746
                                                                                                                 NBA=NB+78
                                                                                                                                                      NBA=NB+77
                                                                                                                                                                                                                                             CONTINUE
                         GO TO 24
115 CONTINUE
                                                                                                                                                                                                                                                          GO TO 24
                                                                                                                                                                                                                                                                                                          KV=KV-1
                                     810 NA=NB/2
                                                                                                                                                                                                                                                                                                                                                                                                                            KW=KW-1
                                                    NKW=KW
                                                                                                                                                                                                                                                                                                                                                                                                    K N = N K N
                                                                           743
                                                                                                                                                                                                                                                                                                                                                             762
                                                                742
                                                                                                                                          744
                                                                                                                                                      748
                                                                                                                 745
                                                                                                                                                                                749
                                                                                                                                                                                                                                                                                                                                                                          764
                                                                                                                                                                                                                                                                                                                                                                                                   120
                                                                                                                                                                                                                                                                                                                                                                                                                                         330811
                                                                                                                                                                                                                                                                                                                                                                                                                                                                              813
                                                                                        747
                                                                                                                                                                                                                                                                                                                                                                                       781
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          814
812
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   760
                                                                                                                                                                                           746
                                                                                                                                                                                                                    756
757
                                                                                                                                                                                                       751
                                                                                                                                                                                                                                                                                                                       758
                                                                                                                                                                                                                                                                                                                                   761
```

```
CHECKED ALL BREAKS TO THE RIGHT ON BOTTOM
                                                                                              VAPORIZED SEGMENTS REMOVED FROM SYSTEM
                                                                                                                                                                                                                                                                                                                                                                                                                                                           IF(L(ML,NBAKW)-2)421,345,345
                                                       IF (1-L(ML,NBAKK))765,765,772
                                                                                                                                                                                                                                                                                                                [F(1-L(ML,NB-78))411,411,412
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           IF(2-L(ML,NB-78))353,354,353
                                                                                                                                                                                                              IF (1-L(ML,NB-78))403,403,404
                                                                                                                                                                                                                             IF(1-L(ML,NB-77))405,405,24
L(ML,NB-77)=2
                                                                                                                                                                                                                                                                                                                              IF (1-L(ML,NB-79))413,413,24
                                                                                                                                                                                                                                                                                                                                                                                                                              IF(NB+KW-156)341,341,345
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             IF(2*NA-NB)351,352,351
                                                                                                                                                                                                 F(2*NA-NB)401,402,401
                                                                                                                                                       IF (LOPP)339,339,410
                                                                                                                           IF (NB-156)10,10,14
                                                                                                                                        [F(LOP)29,29,951
             IF (KB) 24, 24, 252
                          DO 765 KK=1,4KB
                                                                                                                                                                                                                                                                                                                                                                                                  MOLECULE IS BROKEN
                                                                                                                                                                                                                                                                                                                                                                                                                 410 DO 421 KW=1,5
                                                                                 L(ML,NBAKK)=2
                                                                                                                                                                                                                                                                     L (ML + NB-78)=2
                                                                                                                                                                                                                                                                                                                                           L(ML,NB-79)=2
                                                                                                                                                                                                                                                                                                                                                                      L(ML,NB-78)=2
                                                                     BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                                                                                                             NBAKW=NB+KW
                                        NBAKK=NW-KK
                                                                                                                                                                                                                                                                                                                                                                                     420 L(ML,NB)=2
                                                                                                                                                                                                                                                                                   L(ML,NB)=2
                                                                                                                                                                     .(ML,NB)=1
                                                                                                                                                                                                                                                                                                  GO TO 410
                                                                                                                                                                                                                                                                                                                                                          GO TO 420
                                                                                                                                                                                                                                                        GO TO 406
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    GO TO 981
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           NBA=NB-77
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        GO TO 360
                                                                                                              GO TO 24
                                                                                                                                                                                                                                                                                                                                                                                                                                                                         CONTINUE
KB-NW-NX
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    NA=NB/2
                                                                                                                                                                                   NA=NB/2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  NYN=KN
                                                       770
772
765
                                                                                                                                                                                                                              404
                                                                                                                                                                                                                                                                                     406
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            351
                                                                                                                                                                                                               401
                                                                                                                                                                                                                                                                      403
                                                                                                                                                                                                                                                                                                                                             413
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               350
                                                                                                                                                                                                                                                                                                                  405
                                                                                                                                                                                                                                                                                                                              412
                                                                                                                                                                                                                                                                                                                                                                       411
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    345
             270
                                                                                                                                                                                                                                                                                                                                                                                                                                340
                                                                                                                                                                                                                                                                                                                                                                                                                                                           343
                                                                                                                                                                                                                                                                                                                                                                                                                                             341
                                                                                                                                                       951
```

```
RIGHT ON TOP
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                C VAPORIZED SEGMENTS REMOVED FROM SYSTEM
                        IF(2-L(ML,NB-78))355,356,355
                                                                                                                  IF(L(ML,NBAKV)-2)370,363,363
                                                                                                                                                                                                                                                  IF (1-L (ML, NBAKK))380,380,376
                                                                                                                                                                                                                                                                                                                                                                      IF(1-L(ML,NBAKK))347,347,349
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          IF(1-L(ML,NBAKK))280,280,383
                                                                                        IF(NBA+KV-78)362,362,363
                                                                                                                                                                                                                                                                                                                                                                                                            NW=NB-78-(NB-78)/2+157
                                                                                                                                                        C CHECKED ALL BREAKS TO THE
                                                                                                                                                                                                                                                                                                                                                                                                                          NX=NBAKV-NBAKV/2+157
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            IF (LOP) 339,339,952
                                                                                                                                                                                                                                                                                                                                IF (KW) 372,372;346
                                                                                                                                                                                                                                                                                                                                                                                                                                                   IF(KB)981,981,358
                                                                                                                                                                                                            IF (KV) 342,342,373
                                                                                                                                                                                                                          DO 380 KK=1,KV
                                                                                                                                                                                                                                                                                                                                             DO 347 KK=1, KW
                                                                                                                                                                                                                                                                                                                                                                                                                                                                 DO 280 KK=1,KB
                                                                                                                                                                     E(KV)=E(KV)+1.
                                                                                                                                                                                                                                                                                                      E(KW) = E(KW) + 1
                                                                             DO 370 KV=1,5
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  L(ML,NBAKK)=2
                                                                                                                                                                                                                                                                           L(ML,NBAKK)=2
                                                                                                                                                                                                                                                                                                                                                                                                L(ML,NBAKK)=2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                             NBAKK=NW-1+KK
                                                                                                     NBAKV=NBA+KV
                                                                                                                                                                                   NBAKV=NBA+KV
                                                                                                                                                                                                                                        NBAKK=NBA+KK
                                                                                                                                                                                                                                                                BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                                                    BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                          NBAKK=NB+KK
            GO TO 360
                                      NBA=NB-79
                                                    60 TO 360
                                                               NBA=NB-78
                                                                                                                                            GO TO 981
NBA=NB-78
                                                                                                                             CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                       KB=NX-NW
                                                                                                                                                                                                                                                                                                                    KW=KW-1
                                                                                                                                                                                                 KV = KV - 1
                                                                                                                                                                                                                                                                                          KW-NKW
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          381
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       383
354
                          352
                                     355
                                                                                                                                                                                                                                                     374
                                                                                                                                                                                                                                                                                                                                 344
                                                                                                                                                                                                                                                                376
                                                                                                                                                                                                                                                                            380
                                                                                                                                                                                                                                                                                                                                             346
                                                                                                                                                                                                                                                                                                                                                                                  349
                                                                                                                                                                                                                                                                                                                                                                                               347
                                                                 356
                                                                                                                                                                                                                                                                                        342
                                                                                                                                                                                                                                                                                                                                                                       348
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    280
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             981
                                                                              360
                                                                                                     362
                                                                                                                    365
                                                                                                                                                                                                                                                                                                                                                                                                                                                                358
                                                                                         361
                                                                                                                                                                                                               371
                                                                                                                                                                                                                          373
                                                                                                                                                                                                                                                                                                                                                                                                                                                    281
```

```
C CHECKED ALL BREAKS TO THE LEFT ON TOP
                                                                         CHECKED ALL BREAKS TO LEFT ON BOTTOM
                                                                                                                                                                                                IF(2-L(ML,NB-78))605,606,605
                                                                                                                                                                                                                                                                                                                                                                                                             IF(1-L(ML,NBAKK))640,640,635
                                               IF (L(ML,NBAKW)-2)390,392,392
                                                                                                                                    IF (2-L(ML,NB-78))603,604,603
                                                                                                                                                                                                                                                                                      F(L(ML,NBAKV)-2)620,612,612
                       IF (NB-KW-78)392,392,386
                                                                                                                         IF(2*NA-NB)601,602,601
                                                                                                                                                                                                                                                            IF(NBA-KV)612,612,613
IF(LOPP)339,339,24
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      IF (KW)631,631,393
                                                                                                                                                                                                                                                                                                                                                                        F(KV)388,388,632
                                                                                                                                                                                                                                                                                                                                                                                      DO 640 KK=1,KV
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  DO 399 KK=1*KW
                                                                                                                                                                                                                                                                                                                                    E(KV)=E(KV)+1.
                                                                                                                                                                                                                                                                                                                                                                                                                                                              E(KW)=E(KW)+1
           DO 390 KW=1,5
                                                                                                                                                                                                                                                 DO 620 KV=1,5
                                                                                                                                                                                                                                                                                                                                                                                                                                      L (ML , NBAKK) = 2
                                                                                                                                                                                                                                                                          NBAKV=NBA-KV
                                                                                                                                                                                                                                                                                                                                                 NBAKV=NBA-KV
                                                                                                                                                                                                                                                                                                                                                                                                                           BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                                                                  NBAKK=NBA-KK
                                   NBAKW=NB-KW
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              NBAKK=NB-KK
                                                                                                                                                             GO TO 610
NBA=NB-78
                                                                                                                                                                                    GO TO 610
                                                                                                                                                                                                                        GO TO 610
                                                                                                                                                                                                                                     NBA=NB-78
                                                                                                                                                                                                           NBA=NB-79
                                                                                                                                                                                                                                                                                                 CONTINUE
GO TO 24
                                                                                                                                                 NBA=NB-77
                                                           CONTINUE
                                                                                    GO TO 24
                                                                                                                                                                                                                                                                                                                                                             < V=KV-1
                                                                                                 NA=NB/2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                           \V = K V - 1
                                                                                                                                                                                                                                                                                                                                                                                                                                                   XXU=XX
                                                                                                             NK W = K M
                                                                                                                                                                                                                                                                                                                                                                                                              634
                                                                                                                                                                                                                                                                                                                                                                                                                         635
                                                            390
                                                                                                                                                                                                                                                                                                                                                                                                                                       640
                                                                                                                                                                                                            609
                                                                                                                                                                                                                                      909
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       391
393
                                                                                                 392
                                                                                                                                                  603
                                                                                                                                                                         604
                                                                                                                                                                                                 602
                                                                                                                                    601
                                                                                                                                                                                                                                                  610
                                                                                                                                                                                                                                                                         613
                                                                                                                                                                                                                                                                                                                                                                          630
952
339
                       384
                                   386
                                                                                                                                                                                                                                                                                      614
                                                                                                                                                                                                                                                                                                  620
                                               387
                                                                                                                                                                                                                                                              611
```

```
07059000
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  07050002
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   -070SQU01
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      ا
گ
                                                                                                                                                                                                                                                                                                                                   VOL=E(1)*14.+E(2)*28.+E(3)*42.+E(4)*56.+E(5)*70.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 WRITE OUTPUT TAPE 3,30,PCVOL,TIME,DWT,NDUP,VOL
                                                                                                                                                                                                                                                                                                        TIME=LOGF(19600./(19600.-800.*XI+DUPN-BVOL))
                                                                                                                                                                          VAPORIZED SEGMENTS REMOVED FROM SYSTEM
                                                                                                                                                                                                                                                                                                                       C MOLECULAR WEIGHT OF EACH ATOM IS 14
                                                                                                                                                                                                                                                                                                                                                                                                                                        DWT = (A(IX) - A(IY))/(T(IX) - T(IY))
IF(1-L(ML,NBAKK))399,399,395
                                                                                                                                 IF(1-L(ML,NBAKK))660,660,662
                                                                                                                                                                                                                                                                                                                                                     PCVOL=100.*VOL/(158.*1400.)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  FORMAT(1X,3F20.6,115,F20.2)
                                                                                                                                                                                                         IF(L(ML,NB)-1)688,11,11
                                                          NX=NB-78-(NB-78)/2+157
                                                                                                                                                                                                                                                                                                                                                                     DIMENSION A(70),T(70)
                                           NW=NBAKV-NBAKV/2+157
                                                                                                                                                                                                                                                                                                                                                                                                               IF(IX-1)691,691,692
                                                                                       IF(KB)24,24,259
                                                                                                                                                                                                                                                                                                                                                                                                                                                                        DWT = A(IX)/T(IX)
                                                                                                     DO 660 KK=1,KB
                                                                                                                                                              L (ML, NBAKK)=2
                              L(ML,NBAKK)=2
                 BVOL=BVOL+1.
                                                                                                                                                BVOL=BVOL+1.
                                                                                                                     NBAKK=NX-KK
                                                                                                                                                                                                                                                    NDUP=NDUP+1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           -2
                                                                                                                                                                                                                                                                                                                                                                                                   T(IX)=TIME
                                                                                                                                                                                                                         L (ML , NB)=1
                                                                                                                                                                                                                                                                                                                                                                                                                                                        GO TO 695
                                                                                                                                                                                                                                                                                               DUPN=NDUP
                                                                                                                                                                                                                                                                                                                                                                                    A(IX)=VOL
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                CALL EXIT
                                                                                                                                                                                                                                       GO TO 24
                                                                           KB=NX-NW
                                                                                                                                                                                             GO TO 24
                                                                                                                                                                                                                                                                  CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   BONITNOD
                                                                                                                                                                                                                                                                                                                                                                                                                              IY = IX - 1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           *J -9(NZ5GA
                                                                                                                                                                                                                                                                                 XI = IX
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                END
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         *U7(P($T
                                                                                                                                                                 099
                                                                                                                                                                                                                                                                                                                                                                                                                 069
                                                                                                                                                                                                                                                                                                                                                                                                                               692
                                                                                                                                                 662
                                                                                                                                                                                                             14
                                                                                                                                                                                                                         688
                                                                                                                                                                                                                                                       11
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     30
                                399
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      695
               395
                                                                                                                                                                                                                                                                                                                                                                                                                                                                         691
                                                                                          290
259
```

APPENDIX IV

COMPUTER PROGRAM

VAPORIZATION OF LADDER POLYMER

COMPLEX CASE - TYPE I

```
3,4, OR 5, THEN GAG=1 AND
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        C IND=0 MEANS NO VAPORIZATION HAS OCCURED. IND=1 MEANS VAPORIZ. OCCURED.
                                                                                                                                                                           2),497(5,1,1),502(0,1,1),503(0,1,1),702(9,0,0),706(5,1,1),511(5,1,1
                                                                                                                                                   1),480(9,1,1),426(0,2,1),430(0,2,1),482(0,0,9),486(5,1,1),489(5,1,1
                                                                                                                          FREQUENCY 1(0,1,5),2(1,0,2),8(9,1,1),400(0,2,1),404(0,2,1),4(1,0,1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   ADJACENT BROKEN MOLECULE=2 VAPORIZED BOND FROM OPPOS. BROKEN MOL.=4
                                                FORMAT (8X,5HPCVOL,12X,4HTIME,11X,3HDWT,11X,4HNDUP,6X,3HVOL,
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            OPPOSITE BROKEN MOLECULE=3
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             WHEN OPPISITE BOND IS ALREADY 2. IT BECOMES 5 RATHER THAN 3
                                                                                                                                                                                                                                COMMON L'NB'NBA'E'BVOL'IEE'IND'LA'LB'LC'ML'GOG'GAG
                                                                                                                                                                                                        3),531(5,1,1),541(0,1,1),542(0,1,1),600(0,1,9)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   IF NBA IS ORIGINALLY 3,4,0R 5 AND NBA+LB-LA IS
C25 TYPE I COMPLEX-10 ATOMS OR LESS VOLATILE
                                                                       10X, 4HBVOL,12X,1HE,11X,2HEE,9X,2HXI)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    IF(L(ML,NB+66)-2)711,712,741
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               BROKEN BOND=1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              8 IF(L(ML,NB+66)-1)12,13,13
                     WRITE OUTPUT TAPE 3,111
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            IF(1-L(ML,NB))11,11,7
                                                                                                     DIMENSION L(100,200)
                                                                                                                                                                                                                                                                                                               R=RAND1(Y)*19900.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           400 IF(IND)12,12,402
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 CALL MVAP (0,1,0)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        CHECK OPPOSITE BOND
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     C MOLECULEE IS BROKEN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               IF(NB-66)8,8,4
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               C CHECK TO LEFT NEXT
                                                                                                                                                                                                                                                                                     DO 24 I=1,600
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               L(ML,NB+66)=5
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             L(ML,NB+66)=3
                                                                                                                                                                                                                                                             DO 25 IX=1,25
                                                                                                                                                                                                                                                                                                                                                                                          NB=199*ML-NR
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          C UNBROKEN BOND=0
C ADJACENT BROKEN
                                                                                                                                                                                                                                                                                                                                                                   ML=NR/199+1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           L(ML,NB)=3
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       L(ML,NB)=1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         GO TO 713
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     NBA=NB+66
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           GAG=60G
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   AND IEE=1.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    GOG=1.
                                                                                                                                                                                                                                                                                                                                                                                                                     GAG=0
                                                                                                                                                                                                                                                                                                                                                                                                                                            0=909
                                                                                                                                                                                                                                                                                                                                                                                                                                                                       LC=0
                                                                                                                                                                                                                                                                                                                                         NR=R
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       713
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             711
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 712
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    741
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             U
```

```
402 NBA=NB+66
IF(L(ML,NB+66)-1)405,900,900
CHECK TO RIGHT NEXT
                                                                                                                                                                                                                (F(L(ML,NB-66)-2)714,715,744
                                                                                                                                                                                                                                                                                                                                                                                                                                    F(L(ML,NB-66)-1)431,901,901
                                                                                                                                                                       480 IF(L(ML,NB-66)-1)420,421,421
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            IF(NB-K-133)483,484,484
                                                                                                                                                            IF(NB-132)480,480,481
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  BROKEN BOND IS CROSSLINK
                                                                                                                                                                                                                                                                                                                                                      IF (IND) 420,420,428
                                                                                                                                                                                     CHECKED OPPOSITE BOND
                                                                                         CALL MVAP (1,0,67)
                                                                                                       IF(IND)405,405,24
                                                                                                                                 CALL MLNK (1,0,67)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                CALL MVAP(1,0,67)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                             IF(IND)431,431,24
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     CALL MLNK (1,0,67)
                                                                                                                                                                                                                                                                                                                                                                                            CALL MLNK (0,1,0)
                           CALL MLNK(0:1:0)
                                                                                                                                                                                                                                                                                                                                       CALL MVAP (0,1,0)
                                                                                                                                                                                                                                                                                                                                                                                                                        CHECK TO RIGHT NEXT
                                                                                                                                                                                                                                                                                 C MOLECULE IS BROKEN
                                                                                                                                                                                                                                                                                                           C CHECK TO LEFT NEXT
                                                                                                                                                                                                                                                                       L(ML,NB-66)=3
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              481 DO 485 K=1,67
                                                                                                                                                                                                                               L(ML,NB-66)=5
                                                                                                                                                                                                   L(ML,NB)=3
                                                                                                                                                                                                                                                                                                 NBA=NB-66
                                                                                                                                                                                                                                                                                                                                                                                                            NBA=NB-66
NBA=NB+66
                                                                                                                                                                                                                                            GO TO 716
                                                                                                                                                                                                                                                                                                                                                                   NBA=NB-66
                                                                                                                                              GO TO 24
                                                                            900 GAG=GOG
                                                                                                                                                                                                                                                                                                                                                                                                                                                    GAG=60G
                                                                                                                                                                                                                                                                                                                            GAG=60G
                                                                                                                                                                                                                                                         GOG=1.
                                                                                                                                                                                                                                                                                                                                                                                 GAG=0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          GAG=0
                                                                                                                    GAG=0
             GAG=0
12
                                                                                                                                                                                                                                                                                                                                                                                                            4.28
                                                                                                         404
                                                                                                                    405
                                                                                                                                                                                                                                                                                                                                                       426
                                                                                                                                                                                                                                                                                                                                                                   420
                                                                                                                                                               4
                                                                                                                                                                                                                                                                                                                                                                                                                                                     901
                                                                                                                                                                                                                                                                                                716
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           431
                                                                                                                                                                                                                                715
                                                                U
                                                                                                                                                                                        O
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     U
```

```
NB IS CROSSLINK.
                                                                                                                                                                                                                                         - NB MORE THAN 66
                                                                                                                                    MUST ALSO CHECK ASSUMED NB FOR GAG WHEN ORIGINAL
                                                                                                                                                 LC=1 IF NB IS 3,4, OR 5 AND NB + LB-LA IS 3,4, OR
                                                                                                                         - NB LESS 66
                                                                                                                         CHECKED ADJACENT BONDS TO THE LEFT
                                                                                                                                                                                                                                         CHECKED OPPOSITE BONDS TO THE LEFT
                         CHECKED
IF(L(ML,NBK)-1)487,485,485
                                                                                                                                                                                                                                                                                                                                                                                                                      IF(L(ML,NB2)-2)644,644,645
                                                                                                                                                                                                                                                                                                                   IF(L(ML,NB1)-2)640,640,641
                                                             IF(L(ML,NX)-1)488,490,490
                                                                                                                                                                                        IF(L(ML,NX)-1)496,498,498
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          IF(NB+K-199)703,703,704
                        THE LEFT
                                                                                                                                                                                                                                                                             IF (NB1) 503,503,504
                                                                                                                                                                                                                                                                                                                                                                                 IF (NB2)800,800,506
                                                                                                                                                                                                                                                                                                                                                                     CALL MLNK(1,0,67)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                        CALL MLNK(1,0,67)
                        CROSSLINKS TO
                                                                                                                                                              495 DO 496 KK=1,K
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              DO 705 K=1,67
                                     DO 488 KK=1,K
                                                 NX=NB-132-KK
                                                                                                                                                                           NX=NB-66-KK
                                                                                                                                                                                                               NB2=0
GO TO 500
                                                                                                                                                                                                                                                                                                                                                                                                                                               GO TO 646
LC=1
                                                                                     NB1=0
GO TO 495
                                                                                                                                                                                                                                                                                                                                             GO TO 642
           CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 GO TO 24
                                                                                                                                                                                                    CONTINUE
                                                                          CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    NB=NBA1
                                                                                                                                                                                                                                                                 NBA1=NB
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       NX=NB+K
                                                                                                           490 NB1=NX
                                                                                                                                                                                                                                                                                           NB=NB1
                                                                                                                                                                                                                                                                                                                                                                                             NB=NB2
                                                                                                                                                                                                                                                     498 NB2=NX
                                                                                                                                                                                                                                                                                                                                                         LC=1
                                                                                                                                                                                                                                                                                                                                                                                                                                    LC=0
                                                                                                                                                                                                                                                                                                       GAG=0
                                                                                                                                                                                                                                                                                                                                                                                                         GAG=0
                                                                                                                                                                                                                                                                                                                                 CC=0
                                                                                                                                                                                        497
                                                                                                                                                                                                   964
                                                                                                                                                                                                                                                                                           504
                                                                                                                                                                                                                                                                   500
                                                                                                                                                                                                                                                                             502
                                                                                                                                                                                                                                                                                                                                                                                 503
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          702
           485
                                                              489
                                                                                                                                                                                                                                                                                                                                 640
                                                                                                                                                                                                                                                                                                                                                                                             506
                                                                                                                                                                                                                                                                                                                                                                                                                                   944
                                                                                                                                                                                                                                                                                                                                                                                                                                                            645
                                                                                                                                                                                                                                                                                                                                                                                                                                                                        949
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   800
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              483
                                                                         488
                                                                                                                                                                                                                                                                                                                                                                     642
                                     487
                                                                                                                                                                                                                                                                                                                                                         641
```

```
- NB MORE THAN 66
                                                                                                                     99
                                                                                                                                                                                                                                                                                                                                                                                                                                                                TIME=LOGF(19900•/(19900•-600•*XI+DUPN-BVOL))
                                                                                                                     NB LESS
                                                                                                                     R I GHT
                    CROSSLINKS TO THE RIGHT CHECKED
                                                                                                                                                                                              CHECKED OPPOSITE BOND TO THE RIGHT
                                                                                                                                                                                                                                                                IF(L(ML,NB3)-2)780,780,781
                                                                                                                                                                                                                                                                                                                                           IF(L(ML,NB4)-2)790,790,791
                                                                                                                    CHECKED ADJACENT BONDS TO THE
                                                                IF(L(ML,NX)-1)550,513,513
                                                                                                                                                    IF(L(ML,NX)-1)551,533,533
IF(L(ML,NX)-1)710,705,705
                                                                                                                                                                                                                                                                                                                     IF(NB4)544,544,545
                                                                                                                                                                                                                               IF(NB3)542,542,543
                                                                                                                                                                                                                                                                                                       CALL MLNK(0,1,0)
                                                                                                                                                                                                                                                                                                                                                                                      CALL MLNK(0,1,0)
                                                                                                                               DO 551 KK=1,K
                                          DO 550 KK=1,K
                                                    NX=NB-133+KK
                                                                                                                                         NX=NB-67+KK
                                                                                                                                                                                                                                                                                                                                                                                                                     NDUP=NDUP+1
                                                                                                GO TO 530
                                                                                                                                                                                    GO TO 540
                                                                                                                                                                                                                                                                                     GO TO 782
                                                                                                                                                                                                                                                                                                                                                                 GO TO 792
                                                                                                                                                                                                                                                                                                                                                                                                                                                       DUPN=NDUP
                                                                                                                                                                                                                                                                                                                                                                                                           GO TO 24
         CONTINUE
                                                                                                                                                               CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                CONTINUE
                                                                          CONTINUE
                                                                                                                                                                                                                     NBA1=NB
                                                                                                                                                                                                                                                                                                                                                                                                NB=NBA1
                                                                                                         NB3=NX
                                                                                                                                                                                                                                                                                                                                NB=NB4
                                                                                                                                                                                                                                         NB=NB3
                                                                                                                                                                                                          533 NB4=NX
                                                                                                                                                                                                                                                                          LC=0
                                                                                                                                                                                                                                                                                                                                                                          LC=1
                                                                                     NB3=0
                                                                                                                                                                          NB4=0
                                                                                                                                                                                                                                                     GAG=0
                                                                                                                                                                                                                                                                                                LC=1
                                                                                                                                                                                                                                                                                                                                                      1C=0
                                                                                                                                                                                                                                                                                                                                                                                                                                            XI = IX
                                ドードー1
                                                                                                                               530
                                                                                                           513
                                                                                                                                                    531
551
                                                                                                                                                                                                                     540
                                                                                                                                                                                                                                                                                                                     545
                                                                                                                                                                                                                                                                                                                                                                                                                                 24
                                                                         550
                                                                                                                                                                                                                                541
                                                                                                                                                                                                                                          543
                                                                                                                                                                                                                                                                                                                                545
                                                                                                                                                                                                                                                                                                                                                      190
                                                                                                                                                                                                                                                                                                                                                                                                 544
                                                                                                                                                                                                                                                                                                                                                                                                                      11
                                                                                                                                                                                                                                                                           780
706
                    ALL
                                                                511
                                                                                                                                                                                                                                                                                                781
                                                                                                                                                                                                                                                                                                          782
                                                                                                                                                                                                                                                                                                                                                                           791
                                                                                                                                                                                                                                                                                                                                                                                      792
                      Ü
                                                                                                                     U
                                                                                                                                                                                                 O
```

```
IF ((LB-LA)*NB+(LA-LB)*K*(1-2*LA)+67*LA+66*(NB/67)*(LA-LB))35,35
                                                                                                                                                                                                                                                                                                             FREQUENCY 30(1:1:9):33(1:0:1):39(1:1:9):44(5:1:1):801(5:1:1):
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         IF((LB-LA)*NBA+(LA-LB)*K*(1-2*LA)+67*LA+66*(NBA/67)*(LA-LB))
                                                                                                                                                                                    WRITE OUTPUT TAPE 3,30,PCVOL,TIME,DWT,NDUP,VOL,BVOL,E,EE,XI
                                                                                                                                                                                                                                                                                                                               .52(1,0,1),802(5,1,1),59(1,0,1),363(5,1,1)
COMMON L,NB,NBA,E,BVOL,IEE,IND,LA,LB,LC,ML,GOG,GAG
                                                                                                                                                                                                                                                                                                                                                                                                     CHECK IF BROKEN MOLECULE RESULTS IN VAPORIZATION
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   CHECKED FOR BROKEN MOLECULE ON ADJACENT SIDE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    CHECKED FOR BROKEN MOLECULE ON OPPOSITE SIDE
                                                                                                                              DWT=(A(IX)-A(IY))/(T(IX)-T(IY))
                                                                                                                                                                                                      FORMAT(1X,3F16.6,110,5F12.1)
                                                                                                                                                                                                                                                                           SUBROUTINE MVAP(LAD, LBD, LCD)
                   PCVOL=100.*VOL/(1400.*134.)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                              IF(L(ML,NBK)-2)29,29,35
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               IF(L(ML,NBK)-2)38,38,43
                                   DIMENSION A(70) +T(70)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        44 IF(LN+LN1-10)46,46,45
                                                                                                                                                                                                                                                                                            DIMENSION L(100,200)
                                                                                          IF(IX-1)601,601,602
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               NBK=NBA+(LA-LB)*K
                                                                                                                                                                                                                                                                                                                                                                                                                                                            NBK=NB+(LA-LB)*K
                                                                                                                                                                   DWT=A(IX)/T(IX)
VOL=14.*(E-EE)
                                                                                                                                                                                                                                                                                                                                                                                                                          DO 29 K=1,7
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        DO 38 K=1,7
                                                                          T(IX)=TIME
                                                                                                                                                                                                                      CONTINUE
CALL EXIT
                                                                                                                                               GO TO 603
                                                       A(IX) = VOL
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            1 43,43,41
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                CONTINUE
GO TO 45
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               29 CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     GO TO 45
                                                                                                            I Y = I X - I
                                                                                                                                                                                                                                                                                                                                                                                     LB=LBD
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       43 LN1=K
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       LN#K
                                                                                                                                                                                                                                                          END
                                                                                                                                                                                   603
30
25
                                                                                           900
                                                                                                            602
                                                                                                                                                                                                                                                                                                                                                                                                                                                                              33
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       35
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            39
                                                                                                                                                                                                                                                                                                                                                                                                                                            30
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                38
                                                                                                                                                                   601
                                                                                                                                                                                                                                                                                                                                                                                                       Ü
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    U
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      U
```

```
IF((LB-LA)*NBA+(LA-LB)*(1-2*LA)+67*LA+66*(NBA/67)*(LA-LB))780;
                                                          (1-2*LA)+67*LA+66*(NB/67)*(LA-LB))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   NYY=NB+132+LB+(LA-LB)*K-(NB/67)*(66)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 SUBROUTINE MLNK (LAD, LBD, LCD)
                                                                                                             IF(L(ML,NLN)-2)946,946,920
                                                                                                                                                                                                                                                                                                                                                                     IF(L(ML,NLN)-2)756,756,780
                                                                                                                                                                                                                          IF(L(ML,NLN)-5)800,50,800
                                                                                                                                                                                                                                                                                                                                                                                                                                                                     IF (L(ML,NLN)-5)811,80,811
                                                                                                                                                                                                          IF(L(ML,NLN)-2)54,50,54
                                                                                                                                                                           IF(L(ML,NLN)-1)51,52,52
                                                                                                                                                                                                                                                                                                                                                                                                                    IF(L(ML,NLN)-1)58,59,59
                                                                                                                                                                                                                                                                                                                                                                                                                                                     IF(L(ML,NLN)-2)60,80,60
                                                                                                                                                                                                                                                                                                                                                                                                      NLN=NBA+(LA-LB)*K+LB-LA
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   IF(L(ML,NYY)-1)63,57,57
                                                            IF ((LB-LA)*NB+(LA-LB)*
                                                                                                                                                           NLN=NB+(LA-LB)*K+LB-LA
                                                                                                                                                                                                                                                                          C VAPORIZED ADJACENT BONDS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    C VAPORIZED OPPOSITE BONDS
                                                                                                                                                                                                                                                                                        IF(LN1-1)756,721,756
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                DIMENSION L(100,200)
                               IF(LN-1)946,901,946
                                              IF(LC)946,946,902
                                                                                                                                            MOLECULE HAS VAPORIZED
                                                                                                                                                                                                                                                                                                       IF (GAG) 756, 756, 725
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  VAPORIZED CROSSLINKS
                                                                                                                              DO 50 K=1,LN
                                                                                               NLN=NB+LB-LA
                                                                                                                                                                                                                                                                                                                                                      NLN=NBA+LB-LA
                                                                                                                                                                                                                                                                                                                                                                                       DO 57 K=1,LN1
                                                                               920,920,905
                                                                                                                                                                                             BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                                                                                                      BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   BVOL=BVOL+1.
                                                                                                                                                                                                                                                            L ( ML , NLN ) =4
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  L (ML,NYY)=4
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      L ( ML , NLN ) =4
                                                                                                                                                                                                                                                                                                                                        1780,758
                                                                                                                                                                                                                                            E=E+1.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      E=E+1•
               RETURN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   RETURN
 IND=0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    780 IND=1
                                                                                                                                                                                                                                                            50
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      363
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  57
                                                              902
45
                                                                                               906
                                                                                                                               946
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   63
                                                                                                                                                                                                                                                                                                                                                                                                                       8
0
7
7
8
7
9
9
                                                                                                                                                                             801
                                                                                                                                                                                                                                           800
                                                                                                                                                                                                                                                                                                                                                                                       756
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       811
                                                                                                                                                                                                                                                                                                                                                        758
                                                                                                                                                                                                                            54
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      80
                                                                                                                                                                                                            52
                                                                                                                                                                                                                                                                                                                                                                                                                                                                        09
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    Ü
```

```
1105(0,1,2),815(5,1,1),133(5,1,1),156(5,1,1),161(5,1,1),163(6,1,1),
FREQUENCY 100(1,1,9),106(5,1,1),107(0,1,1),810(5,1,1),811(0,1,1),
                                                                                                                                                                                                                                                                                                                                                                       BOND IS BROKEN TO GIVE BROKEN MOLECULE
                                                   COMMON L, N3, NBA, E, BVOL, IEE, IND, LA, LB, LC, ML, GOG, GAG
                                                                                                       CHECK IF BROKEN CROSSLINKS GIVE BROKEN MOLECULE
                                                                                                                                                                                                                                                                                                                     66+(LA-LB)*KK-(NB/67)*(132)
                                                                                                                                                           IF(200*LA+(LB-LA)*NY-132*LB)105,105,106
                                                                                                                                         NY=NB+132+LB+(LA-LB)*K-(NB/67)*(66)
                                                                                                                                                                                                                                                                                                                                         IF(L(ML,NBA)-1)110,150,150
                                                                                                                                                                                                                                                                                                                                                                                                                            IF(L(ML,NBA)-2)717,718,747
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               IF(L(ML,NLN)-1)132,133,133
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 IF(L(ML,NLN)-2)134,135,120
                                                                                                                                                                              IF(L(ML,NY)-1)107,104,104
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              NLN=NB+(LA-LB)*KK+(LB-LA)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   CALL MVAP (LA, LB, LC)
                                                                                                                                                                                                                                                   IF(K-1)108,108,109
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        IF(IND)151,151,152
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         IF(K-1)130,130,131
                                                                                                                                                                                                                                                                                                                                                                        CHECKED IF OPPOSITE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    C MOLECULE IS BROKEN
                                                                                                                         DO 104 K=1,11
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              DO 120 KK=1,K
                                                                                                                                                                                                                                                                                                       DO 110 KK=1,K
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                                                                                                               L (ML, NBA) = 5
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     . (ML, NBA)=3
                                    2152(0,1,1)
                                                                                                                                                                                                                                                                                                                                                                                                           L(ML,NB)=3
                                                                                                                                                                                                                                                                                                                                                                                                                                                                 GO TO 719
                                                                                                                                                                                                                                   GO TO 109
                                                                                                                                                                                                                                                                                                                                                                                           GO TO 151
                                                                                                                                                                                                 CONTINUE
                                                                                                                                                                                                                                                                                                                                                         110 CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        NBAA=NBA
                                                                                                                                                                                                                                                                                                                         NBA=NB+
                                                                                         LB=LBD
                                                                                                                                                                                                                                                                      RETURN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  GAG=1.
                                                                       LA=LAD
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           RETURN
                                                                                                                                                                                                                                                                                       K=K-1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             K=K-1
                                                                                                                                                                                                                  K=11
                                                                                                                                                                                106
                                                                                                                                                                                                                                                                                                                                                                                                             150
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 815
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           105
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           130
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                132
                                                                                                                                                                                                                                                    107
                                                                                                                                                                                                                                                                      108
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         811
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   719
                                                                                                                                                                                                                                                                                                                                                                                                                                                 718
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  747
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   717
                                                                                                            U
                                                                                                                                                                                                                                                                                                                                                                           Ü
```

```
07050100
                                                                                                                                                                                                                                                                                                                                                                                                                                07059U02
                                                                                                                                                                                                                                                                                                                                                                                                                     -070SQU01
                                                                                                                                                                                                                                                                                                                                                                                                                        7-
                                                                                                                                                                                                                                                                                                                                                                                                                       4E
                                                                                                                                                                                                                                                                                                                                                                                                                          1
                                                                                                                                                                                                                                                                                                                                                                                                                       1
                                                                                                        CHECKED IF ADJACENT BOND IS BROKEN TO GIVE BROKEN MOLECULE
                                                                                                                                                                                                                                                                                                                                                                                                                       5
                                                                                                                                                                                                                                                                                                                                                                                                                         20
                                                                                                                                                                                                                                                                                                                                                                                                                                   0
                                                                                                                                                                                                                                                                                                                                                                                                                        46
                                                                                                                                                                                                                                                       IF(L(ML,NB)-3)650,152,650
IF MOLECULE IS BROKEN,CHECK BOTH DIRECTIONS
                                                                                                                                                                                                                                                                                                                                                                                                                                  2(X)
                                                                                                                                                                                                                                                                                                                                                                                                                        95
                                                                                                                                                                                                                                                                                                                                                                                                                       26
                                                                        IF(L(ML,NBA)-1)155,158,158
                                                                                                                                                                 IF(L(ML,NBA)-2)164,165,166
                                                                                                                                           IF(L(ML,NBA)-1)162,163,163
                                                                                               IF(L(ML,NB)-3)650,152,650
                                                                                                                                 NBA=NB+(LA-LB)*K+LB-LA
                                         VAPORIZED ADJACENT BONDS
                                                                                                                                                                                                            C VAPORIZED ADJACENT BONDS
                                                                                                                                                                                                                                                                                                                                                                             CALL MVAP (LA,LB,LC)
                                                               NBA=NB+(LA-LB)*KK
                                                                                                                                                                                                                                                                                                                                                                                                                                  5484
                                                                                                                                                                                                                                                                          152 IF(LA)200,200,201
                                                                                                                      158 DO 168 K=1,KK
                                                    DO 155 KK=1,K
         L(ML,NLN)=2
                                                                                                                                                                                                 L(ML,NBA)=2
                                                                                                                                                      BVOL=BVOL+1
                                                                                                                                                                                                                                                                                                                                                                                                                         7 1 2
                                                                                                                                                                                                                       GO TO 168
                                                                                                                                                                            IEE=IEE+1
                                                                                      CONTINUE
                                                                                                                                                                                                                                             CONTINUE
                    CONTINUE
                                                                                                                                                                                                                                                                                                                                                                   NBA=NBAA
                                                                                                                                                                                                                                  E=E+1•
                               RETURN
                                                                                                                                                                                       E=E+1.
                                                                                                                                                                                                                                                                                                                                                                                        RETURN
E=E+1
                                                                                                                                                                                                                                                                                                                      G0 T0
                                                                                                                                                                                                                                                                                                                                                                                                                       *J -9(NZ5GA
                                                                                                                                                                                                                                                                                                           LC=67
                                                                                                                                                                                                                                                                                                LB=0
                                                                                                                                                                                                                                                                                                                                 LA=0
                                                                                                                                                                                                                                                                                                                                             L8=1
                                                                                                                                                                                                                                                                                                                                                        1C=0
                                                                                                                                                                                                                                                                                      LA=1
                                                                                                                                                                                                                                                                                                                                                                                                  END
                                                                                                                                                                                                                                                                                                                                                                                                                                  *U7(P($T
                                                                                                                                                                                                                                                                                                                                                                                                              )1 (X-
                                                     151
                                                                           156
                                                                                                                                                                                                                                                                                                                                                                   210
                                                                                                                                                                                                                                                                                                                                                                                         650
134
                    120
                                                                                     155
                                                                                                                                                                 163
                                                                                                                                                                            165
                                                                                                                                                                                                                                                                                      200
                                                                                                                                                                                                                                   166
                                                                                                                                                                                                                                             168
                                                                                                                                                                                                                                                                                                                                  201
                                                                                                                                                       162
                                                                                                            Ü
```

APPENDIX V

COMPUTER PROGRAM

VAPORIZATION OF LADDER POLYMER

COMPLEX CASE - TYPE II

```
1(0,1,5),2(1,0,2),700(1,1,0),40(1,1,5),42(1,1,5),701(1,0
                                                                                                                                                 *1)*802(1*0*1)*41(1*1*5)*721(1*1*5)*724(1*0*1)*722(1*0*1)*400(0*1*
                                                                                                                                                                         21),404(0,1)1),4(1,0,1),740(1,1,0),741(1,1,5),743(1,1,5),743(1,1,5)
                                                                                                                                                                                                  3,751(1,0,1),756(1,1,5),758(1,1,5),760(1,0,1),765(1,0,1)
                                                                                                                                                                                                                                                    5,801(1,0,1),503(0,1,1),803(1,0,1),702(9,1,0),706(5,1,1),511(5,1,1)
                                                                                                                                                                                                                                                                             6,531(5,1,1),541(0,1,1),805(1,0,1),542(0,1,1),806(1,0,1),600(0,1,9)
                                                                                                                                                                                                                            4,773(0,1,1),482(0,1,9),486(5,1,1),489(9,1,1),497(5,1,1),502(0,1,1
                                              FORMAT(8X,5HPCVOL,12X,4HTIME,11X,3HDWT,11X,4HNDUP,6X,3HVOL,10X,
                                                                                                                                                                                                                                                                                                    COMMON L,NB,NBA,E,BVOL,IEE,IND,LA,LB,LC,ML,GOG,GAG
- 10 ATOMS OR LESS VOLATILE
                                                                      (4HBVOL,12X,1HE,11X,2HEE,9X,2HXI)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        IF (L(ML,NB+79)-2)715,716,717
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  F(L(ML,NB+78)-2)711,712,841
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    F(1-L(ML,NB+78))100,100,42
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              F(1-L(ML,NB+79))101,101,21
                       OUTPUT TAPE 3,111
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                F(1-L(ML,NB))11,11,7
                                                                                                  DIMENSION L(100,200)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            IF (2*NA-NB)40,41,40
                                                                                                                                                                                                                                                                                                                                                                                   R=RAND1 (Y) * 19600.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         CHECK OPPOSITE BOND
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             MOLECULE IS BROKEN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 IF(NB-78)8,84
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         L (ML , NB+78)=5
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     L(ML,NB+78)=3
                                                                                                                                                                                                                                                                                                                                  DO 25 IX=1,25
                                                                                                                                                                                                                                                                                                                                                          DO 24 I=1,600
 COMPLEX
                                                                                                                                                                                                                                                                                                                                                                                                                                                             NB=196*ML-NR
                                                                                                                                                                                                                                                                                                                                                                                                                                      ML=NR/196+1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       . (ML.NB)=3
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              L(ML,NB)=3
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           L (ML,NB)=1
                                                                                                                            FREQUENCY
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    50 TO 713
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     NBA=NB+78
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       GO TO 200
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                NNBA=NBA
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    NA=NB/2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          GOG=1.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      GAG=0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                0=909
                                                                                                                                                                                                                                                                                                                                                                                                           NR=R
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         1C=0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        802
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                101
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             841
                                                   111
```

```
IF(L(ML,NB+77)-2)730,731,732
                                                                            GO TO 200
IF(1-L(ML,NB+78))720,720,721
                                                                                                                        IF(L(ML,NB+78)-2)725,726,727
                                                                                                 IF(1-L(ML,NB+77))722,722,21
                                                                                                                                                                                                                                                                                                                                                                                                                                            IF(IND)405,405,24
                                                                                                                                                                                                                                                                                                                                                                                                                                                                 CALL MLNK (1,0,67)
                                                                                                                                                                                                                                                                                                                                                                                                                                CALL MVAP(1,0,67
                                                                                                                                                                                                                                                                                                                                                IF(IND)12,12,402
                                                                                                                                                                                                                                                                                                                                     CALL MVAP(0,1,0)
                                                                                                                                                                                                                                                                                                                                                                                  CALL MLNK(0,1,0)
                                                                                                                                                                                                                                                                                                                                                                                                        C CHECK TO RIGHT NEXT
                                  715 L(ML,NB+79)=3
C MOLECULE IS BROKEN
718 NBA=NB+79
                                                                                                                                                                                C MOLECULE IS BROKEN
                                                                                                                                                                                                                                                                                       C MOLECULE IS BROKEN
                                                                                                                                                                     L(ML,NB+78)=3
L (ML, NB+79)=5
                                                                                                                                   L (ML, NB+78)=5
                                                                                                                                                                                                                                          L (ML,NB+77)=5
                                                                                                                                                                                                                                                                             L (ML,NB+77)=3
                                                                                                              L (ML,NB)=3
                                                                                                                                                                                                                  GO TO 200
             GO TO 718
                                                                                                                                                GO TO 728
                                                                                                                                                                                            NBA=NB+78
                                                                                                                                                                                                                                                      GO TO 733
                                                                                                                                                                                                                                                                                                   NBA=NB+77
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       NBA=NB+78
                                                                                                                                                                                                                                                                                                                                                           NBA=NNBA
                                                                                                                                                                                                                                                                                                                                                                                             NBA=NNBA
                                                                                                                                                                                                                                                                                                                                                                                                                                                                           GO TO 24
                                                                  NNBA=NBA
                                                                                                                                                                                                         NNBA=NBA
                                                                                                                                                                                                                                                                                                               NNBA=NBA
                                                                                                                                                                                                                                                                                                                           GAG=60G
                                                                                                                                                                                                                                                                                                                                                                                                                    GAG=60G
                        606=1.
                                                                                                                                                           GOG=1.
                                                                                                                                                                                                                                                                  606=1.
                                                                                                                                                                                                                                                                                                                                                                       GAG=0
                                                                                                                                                                                                                                                                                                                                                                                                                                                        GAG=0
                                                                                                                                                                                                                                                                                                                                                                                              402
 716
                                                                                                                                                            727
                                                                                                                                                                                             728
                                                                                                                                                                                                                                                                  732
                                                                                                                                                                                                                                                                                                                                                                                                                                                     405
                                                                                                                                                                                                                                                                                                   733
                                                                                                                                                                                                                                                                                                                            200
                                                                                                                                                                                                                                                                                                                                                  400
12
                                                                                                                                                                                                                                                                                                                                                                                                                                             404
                                                                                                                                                                                                                               722
731
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         21
```

```
IF(L(ML,NB-78)-2)761,762,763
L(ML,NB-78)=5
                                                                                                                                                                                                                                                                                                                                                                          F(1-L(ML,NB-78))757,757,758
F(1-L(ML,NB-79))759,759,22
                                                                                                      [F(1-L(ML,NB-78))742,742,743
[F(1-L(ML,NB-77))744,744,22
                                                                                                                                        F(L(ML,NB-78)-2)746,747,748
                                                                                                                                                                                                                                                                 [F(L(ML,NB-77)-2)752,753,754
                                                                                          F(2*NA-NB)741,756,741
                                                                     IF(NB-156)480,480,481
NA=NB/2
                                             CALL MLNK (1,0,67)
          CALL MLNK(0,1,0)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                         C MOLECULE IS BROKEN 764 NBA=NB-78
                                                                                                                                                                                                                                                                                                                           C MOLECULE IS BROKEN 755 NBA=NB-77
                                                                                                                                                                                                    C MOLECULE IS BROKEN
                                                                                                                                                    L(ML,NB+78)=5
                                                                                                                                                                                                                                                                                                                L (ML,NB-77)=3
                                                                                                                                                                                                                                                                                                                                                                                                                                                             L (ML, NB-78)=3
                                                                                                                                                                                         L(ML,NB-78)=3
                                                                                                                                                                                                                                                                            L(ML,NB-77)=5
                                                                                                                                                                                                                                                                                                                                                                                                                                      GO TO 764 -
                                                                                                                              . (ML . NB)=3
                                                                                                                                                                                                                                                    L(ML,NB)=3
                                                                                                                                                                                                                                                                                                                                                                                                  _ (ML,NB)=3
                                                                                                                                                                 GO TO 750
                                                                                                                                                                                                                                                                                        GO TO 755
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     NBA=NB-78
                                   NBA=NB+78
                                                                                                                                                                                                                 NBA=NB-78
                                                                                                                                                                                                                                        GO TO 201
                                                                                                                                                                                                                                                                                                                                                               GO TO-201
                                                          GO TO 24
                                                                                                                                                                                                                                                                                                                                                   NNBA=NBA
                                                                                                                                                                                                                            NNBA=NBA
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  NNBA=NBA
                                                                                                                                                                                                                                                                                                                                                                                                                                                   GOG=1.
                                                                                                                                                                             606=1.
                                                                                                                                                                                                                                                                                                    GOG=1.
                       GAG=0
GAG=0
                                                                                                                                                                                                                 750
                                                                                          740
                                                                                                                                          745
                                                                                                                                                                              748
                                                                                                                                                                                         746
                                                                                                                                                                                                                                                                                                     754
                                                                                                                                                                                                                                                                                                                                                                            756
758
                                                                                                                                                                                                                                                                                                                                                                                                  757
760
762
                                                                                                                                                                                                                                                                                                                                                                                                                                                   763
                                                                                                                                                                                                                                                                                                                                                                                                                                                              761
                                                                                                                 743
                                                                                                                             742
                                                                                                                                                     747
                                                                                                                                                                                                                                                                           753
                                                                                                     741
                                                                                                                                                                                                                                                     744
                                                                                                                                                                                                                                                                 751
```

```
CROSSLINKS TO THE LEFT CHECKED
          IF(L(ML,NB-79)-2)766,767,768
                                                                                                                                                                                                                                                                                                                                                                                                       IF(L(ML,NBK)-1)487,485,485
                                                                                                                                                                                                                                                                                                                                                                                                                                                                           IF(L(ML,NX)-1)488,490,490
                                                                                                                                                                                                                                                                                                                                                                               IF(NB-K-157)483,484,484
                                                                                                                                                                                                                                                                                                                                                       C BROKEN BOND IS A CROSSLINK
                                                                                                                                                                                                                                                                                                                                                                                                                                                                NX=NB-156-KK+NB-157
                                                                                                        GAG=GOG
CALL MVAP(0,1,0)
IF(IND)771,771,772
                                                                                                                                                                                                                        IF(IND)774,774,24
                                                                                                                                                                                                                                                                                                                                  CALL MLNK(1,0,67)
                                                                                                                                                                                                             CALL MVAP(1,0,67)
                                                                                                                                                                                                                                                CALL MLNK (1,0,67)
                                                                                                                                                               CALL MLNK(0,1,0)
                                                                                                                                                                                                                                                                                              CALL MLNK(0,1,0)
                                                                                                                                                                                      C CHECK TO RIGHT NEXT
                                                                   C MOLECULE IS BROKEN
                                                          L (ML, NB-79)=3
                                                                                                                                                                                                                                                                                                                                                                     DO 485 K=1,40
                                                                                                                                                                                                                                                                                                                                                                                                                                                      DO 488 KK=1,K
                       L (ML,NB-79)=5
L (ML,NB)=3
                                                                                                                                                                                                                                                                                                                      NBA=NB+78
                                  GO TO 769
                                                                                 NBA=NB-79
                                                                                                                                                                                                                                                                       NBA=NB-78
                                                                                                                                                                           NBA=NNBA
                                                                                                                                                                                                                                                                                                                                             GO TO 24
                                                                                                                                                                                                                                                                                                                                                                                            NBK=NB-K
                                                                                                                                                                                                                                                                                                                                                                                                                   CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       CONTINUE
                                                                                             NNBA=NBA
                                                                                                                                         NBA=NNBA
                                                                                                                                                                                                                                                            GO TO 24
                                                                                                                                                                                                  GAG=GOG
                                              GOG=1.
                                                                                                                                                                                                                                     GAG=0
                                                                                                                                                                                                                                                                                                           GAG=0
                                                                                                                                                    GAG=0
                                                                                                                                                                                                                                                                                                                                                                                                                                           K=2*K
                                                                                                                                                                                                                                                                                    GAG=0
                                                                                                                                                                                                                                                                                                                                                                                                                               CALL
           765
                       767
                                                           766
                                                                                   492
                                                                                                                                                                           772
                                                                                                                                                                                                                                                                                                                                                                                482
                                                                                                                                                                                                                                                                                                                                                                                            484
                                                                                                                                                                                                                                                                                                                                                                                                       486
                                                                                                                                                                                                                                                                                                                                                                                                                  485
                                                                                                                                                                                                                                                                                                                                                                                                                                                                             489
                                               768
                                                                                                                             770
                                                                                                                                                                                                                         773
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      488
                                                                                                           701
                                                                                                                                        771
                                                                                                                                                                                                                                                                        22
```

```
NB IS CROSSLINK
                                                                                                                                                C CHECKED OPPOSITE BONDS TO THE LEFT-NB MORE THAN 78
                                     C MUST ALSO CHECK ASSUMED NB FOR GAG WHEN ORIGINAL C LC=1 IF NB IS 3,4,0R,5 ANDNB+LB-LA IS 3,4,0R,5
                        C CHECKED ADJACENT BONDS TO THE LEFT-NB LESS 78
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  CROSSLINKS TO THE RIGHT CHECKED
                                                                                                                                                                                                                                                                                                                                     IF(L(ML,NB2)-2)644,644,645
                                                                                                                                                                                                                           IF(L(ML,NB1)-2)640,640,641
                                                                                           IF(L(ML,NX)-1)496,498,498
                                                                                                                                                                                                                                                                                                                                                                                                                                                                       IF(L(ML,NX)-1)710,705,705
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    IF(L(ML,NX)-1)550,513,513
                                                                                                                                                                                                                                                                                                                                                                                                                                             IF(NB+K-196)703,703,704
                                                                             NX=NB-156-KK+NB-157-78
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      NX=NB-157+KK+NB-157
                                                                                                                                                                                 IF(NB1)503,503,504
                                                                                                                                                                                                                                                                                             IF (NB2)800,800,506
                                                                                                                                                                                                                                                                                CALL MLNK(1,0,67)
                                                                                                                                                                                                                                                                                                                                                                                         CALL MLNK (1,0,67)
                                                                 DO 496 KK=1,K
                                                                                                                                                                                                                                                                                                                                                                                                                                DO 705 K=1,40
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          DO 550 KK=1,K
                                                                                                                                  GO TO 500
                                                                                                                                                                                                                                                      GO TO 642
                                                                                                                                                                                                                                                                                                                                                               GO TO 646
GO TO 495
                                                                                                       CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                   GO TO 24
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     CONTINUE
                                                                                                                                                            NB2=NX
NBA1=NB
                                                                                                                                                                                                                                                                                                                                                                                                                                                           NX=NB+K
                                                                                                                                                                                                                                                                                                                                                                                                     NB=NBA1
            NB1=NX
                                                                                                                                                                                                 NB=NB1
                                                                                                                                                                                                                                                                                                          NB=NB2
                                                                                                                    NB2=0
                                                                                                                                                                                                             GAG=0
                                                                                                                                                                                                                                                                                                                        GAG=0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                K=K-1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              X = 2 * K
                                                                                                                                                                                                                                                                   LC=1
                                                                                                                                                                                                                                                                                                                                                  C=0
                                                                                                                                                                                                                                                                                                                                                                            LC=1
                                                                                                                                                                                                                                         LC=0
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  CALL
                                                                  495
                                                                                                                                                            498
500
                                                                                                                                                                                                                                                                                                                                                  644
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     705
                                                                                                                                                                                  502
                                                                                                                                                                                                                                         640
                                                                                                                                                                                                                                                                                                                                                                                         949
                                                                                                                                                                                                                                                                                                                                                                                                      800
                                                                                                                                                                                                                                                                                                                                                                                                                                                          703
                                                                                                                                                                                                                                                                                                                                                                                                                                                                       706
                                                                                           497
                                                                                                         496
                                                                                                                                                                                                                                                                               642
                                                                                                                                                                                                                                                                                             503
                                                                                                                                                                                                                                                                                                                                     803
                                                                                                                                                                                                                                                                                                                                                                             645
                                                                                                                                                                                                                                                                                                                                                                                                                                             702
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    511
                                                                                                                                                                                                                           801
                                                                                                                                                                                                                                                                    641
```

```
C CHECKED OPPOSITE BOND TO THE RIGHT-NB MORE THAN 66
                                                                                                                                                                                                                                                                                                                                                                                                                           TIME=LOGF(19600./(19600.-600.*XI+DUPN-BVOL))
                                           C CHECKED ADJACENT BONDS TO THE RIGHT-NB LESS 66
                                                                                                                                                                                                                                                                                                                                                                                                                                                                PCVOL=100.*VOL/(1400.*158.)
                                                                                                                                                                                                         IF(L(ML,NB3)-2)780,780,781
                                                                                                                                                                                                                                                                                          IF(L(ML,NB4)-2)790,790,791
                                                                                 IF(L(ML,NX)-1)551,533,533
                                                                                                                                                                                                                                                                                                                                                                                                                                                                             DIMENSION A(70), T(70)
                                                                                                                                                                      IF(NB3)542,542,543
                                                                                                                                                                                                                                                                   IF(NB4)544,544,545
                                                                     NX=NB-79+KK+NB-157
                                                                                                                                                                                                                                                        CALL MLNK (0,1,0)
                                                                                                                                                                                                                                                                                                                                         CALL MLNK (0,1,0)
                                                                                                                                                                                                                                                                                                                                                                                                                                                     VOL = 14 . * (E-EE)
                                                        DO 551 KK=1,K
                                                                                                                                                                                                                                                                                                                                                                              NDUP=NDUP+1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    T(IX)=TIME
                      GO TO 530
                                                                                                                    GO TO 540
                                                                                                                                                                                                                                GO TO 782
                                                                                                                                                                                                                                                                                                                 GO TO 792
                                                                                                                                                                                                                                                                                                                                                                                                                  ANGN=NdNC
                                                                                              CONTINUE
                                                                                                                                                                                                                                                                                                                                                                  GO TO 24
CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                         CONTINUE
                                                                                                                                                          NBA1=NB
                                                                                                                                                                                                                                                                                                                                                      NB=NBA1
                                  NB3=NX
                                                                                                                                              NB4=NX
                                                                                                                                                                                 NB=NB3
                                                                                                                                                                                                                                                                              NB=NB4
            NB3=0
                                                                                                          NB4=0
                                                                                                                                                                                                                                                                                                                                                                                                      XI = IX
                                                                                                                                                                                              GAG=0
                                                                                                                                                                                                                                           LC=1
                                                                                                                                                                                                                                                                                                       C=0
                                                                                                                                                                                                                     LC=0
                                                                                                                                                                                                                                                                                                                               LC=1
                                                           530
550
                                                                                   531
                                                                                              551
                                                                                                                                                          540
                                                                                                                                                                                  543
                                                                                                                                                                                                         805
                                                                                                                                                                                                                     780
                                                                                                                                                                                                                                                       782
                                                                                                                                                                                                                                                                              545
                                                                                                                                                                                                                                                                                           806
790
                                                                                                                                                                                                                                                                                                                               791,
792
                                                                                                                                                                      541
                                                                                                                                                                                                                                           781
                                                                                                                                                                                                                                                                    545
                                                                                                                                                                                                                                                                                                                                                      544
```

```
1,5),901(0,1,1,1,902(1,1,5),410(1,0,1),801(3,1,1),52(1,0,1),54(1,1,0
                                                                                                                                                                                                                             FREQUENCY 30(1,1,5),33(1,0,1),39(1,1,5),42(1,0,1),44(5,1,1),46(0,1
                                                                                                                                                                                                                                                               2),920(0,1,5),721(0,1,1),725(1,1,5),420(1,0,1),802(5,1,1),59(1,0,1)
                                                                                                                                                                                                                                                                                                                                                                                                         IF ((LB-LA)*NB+(LA-LB)*K*(1-2*LA)+79*LA+78*(NB/79)*(LA-LB))35
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      IF ((LB-LA)*NBA+(LA-LB)*K*(1-2*LA)+79*LA+78*(NBA/79)*(LA-LB))
                                                                                        3,30,PCVOL,TIME,DWT,NDUP,VOL,BVOL,E,EE,XI
                                                                                                                                                                                                                                                                                                        COMMON L, NB, NBA, E, BVOL, IEE, IND, LA, LB, LC, ML, GOG, GAG
                                                                                                                                                                                                                                                                                                                                                                   C CHECK IF BROKEN MOLECULE RESULTS IN VAPORIZATION DO 29 K=1.7
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         C CHECKED FOR BROKEN MOLECULE ON ADJACENT SIDE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         ON OPPOSITE
                                  DWT=(A(IX)-A(IY))/(T(IX)-T(IY))
                                                                                                             FORMAT(1X,3F16.6,110,5F12.1)
                                                                                                                                                                                            SUBROUTINE MVAP(LAD, LBD, LCD)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          C CHECKED FOR BROKEN MOLECULE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                   IF (L(ML, NBK)-2)29,29,35
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                IF (L(ML, NBK)-2)38,38,43
                                                                                                                                                                                                                                                                                          3,60(1,1,0),363(2,1,1)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               IF (LN+LN1-10)46,46,45
                                                                                                                                                                                                              DIMENSION L(100,200)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         IF(LN-1)946,901,946
F(IX-1)601,601,602
                                                                                            WRITE OUTPUT TAPE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              NBK=NBA+(LA-LB)*K
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            [F(LC)946,946,902
                                                                                                                                                                                                                                                                                                                                                                                                                                                NBK=NB+(LA-LB)*K
                                                                            DWT=A(IX)/T(IX)
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    DO 38_K=1,7
                                                        GO TO 603
                                                                                                                                                        CALL EXIT
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              GO TO 45
                                                                                                                                    CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          143,43,41
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        GO TO 45
                                                                                                                                                                                                                                                                                                                                  LA=LAD
                                                                                                                                                                                                                                                                                                                                                     LB=LBD
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      RETURN
                                                                                                                                                                                                                                                                                                                                                                                                                             135,32
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              LN1=K
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                LN=K
  600
                                                                              601
603
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            901
                                                                                                                                                                                                                                                                                                                                                                                                          9
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      59
                                                                                                                  30
                                                                                                                                                                                                                                                                                                                                                                                                                                                                   33
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 44
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                35
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         39
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               38
```

```
IF((LB-LA)*NB+(LA-LB)*(1-2*LA)+79*LA+78*(NB/79)*(LA-LB))920•
                                                                                                                                                                                                                                                                                       IF((LB-LA)*NBA+(LA-LB)*(1-2*LA)+79*LA+78*(NBA/79)*(LA-LB))
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      NYY=NB+LB+156-NB/2-(NB/79)*39+(LA-LB)*K
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    KC=K/2+KAA*KBB*LB+KAA*(1-KBB)*LA
                                                                                                                                                                                                                                                                                                                                               IF(L(ML,NLN)-2)756,756,780
                                                       IF(L(ML,NLN)-2)946,946,920
                                                                                                                                                                IF(L(ML,NLN)-2)54,50,54
IF(L(ML,NLN)-5)800,50,800
                                                                                                                                                                                                                                                                                                                                                                                                                                                        IF(L(ML,NLN)-5)811,80,811
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          IF(L(ML,NYY)-1)63,400,400
                                                                                                                                                                                                                                                                                                                                                                                                  IF(L(ML,NLN)-1)58,59,59
                                                                                                                                                                                                                                                                                                                                                                                                                                       IF (L(ML,NLN)-2)60,80,60
                                                                                                                                                                                                                                                                                                                                                                                 NLN=NBA+(LA-LB)*K+LB-LA
                                                                                                                              IF(L(ML,NLN)-1)51,52,52
                                                                                                             NLN=NB+(LA-LB)*K+LB-LA
                                                                                                                                                                                                                                                        IF(LN1-1)756,721,756
                                                                                                                                                                                                                                        C VAPORIZED ADJACENT BONDS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            C VAPORIZED OPPOSITE BONDS
                                                                                                                                                                                                                                                                          IF (GAG) 756, 756, 725
                                                                          946 DO 50 K=1,LN
C MOLECULE HAS VAPORIZED
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             C VAPORIZED CROSSLINKS
                                                                                                                                                                                                                                                                                                                              NLN=NBA+LB-LA
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      DO 400 K=1,KC
                                                                                                                                                                                                                                                                                                                                                                  DO 57 K=1,LN1
                                                                                                                                                                                                                                                                                                                                                                                                                     BVOL=BVOL+1.
                                         NLN=NB+LB-LA
                                                                                                                                                  BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    KAA=LN1-2*KA
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                             1780,780,758
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            L (ML, NLN) =4
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  KBB=NB-2*KB
                                                                                                                                                                                                                       L (ML,NLN)=4
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              T ( ML , NYY) =4
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              CONTINUE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                KA=LN1/2
                      1920,905
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  KB=NB/2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                           E=E+1.
                                                                                                                                                                                                      E=E+1•
                                                                                                                                                                                                                                                           920
                                                          410
                                                                                                                                                                                                      800
                                                                                                                                                                                                                                                                            721
                                                                                                                                                                                                                                                                                                                                 758
420
                                                                                                                                                                                                                                                                                                                                                                                                      802
58
59
60
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              400
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           63
```

```
811(0,1,1),105(0,1,5),815(5,1,1),133(1,0,1),156(5,1,1),620(1,0,1),
                                                                     FREQUENCY 100(1,1,5),107(0,1,5),600(0,1,1),810(5,1,1),610(1,0,1),
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           BROKEN TO GIVE BROKEN MOLECULE
                                                                                                                            COMMON L, NB, NBA, E, BVOL, IEE, IND, LA, LB, LC, ML, GOG, GAG
                                                                                                          2161(5,1,1),163(1,0,1),630(1,0,1),152(0,1,1)
                                                                                                                                                                                    C CHECK IF BROKEN CROSSLINK GIVES BROKEN MOLECULE
                                                                                                                                                                                                                                          IF(197*LA+(LB-LA)*NY-156*LB)105,105,106
                                                                                                                                                                                                                        NY=NB+LB+156-NB/2-(NB/79)*39+(LA-LB)*K
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     NBA=NB+78+(LA-LB)*KK-(NB/79)*156
                                    SUBROUTINE MLNK(LAD, LBD, LCD)
                                                                                                                                                                                                                                                                                                                                                                                                IF(LB*(1-KB)+LA*KB)40,41,40
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       IF(L(ML,NBA)-1)110,150,150
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   IF(L(ML,NBA)-2)717,718,747
                                                                                                                                                                                                                                                                 IF(L(ML*NY)-1)107,104,104
                                                                                                                                                                                                                                                                                                                                                                                                                                                     IF(L(ML,NY)-1)240,241,241
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           C CHECKED IF OPPOSITE BOND IS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  K=2*K+LB*(1-KB)+LA*KB
                                                     DIMENSION L(100,200)
                                                                                                                                                                                                                                                                                                                                           IF(K-1)108,108,109
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    DO 110 KK=1,K
                                                                                                                                                                                                          DO 104 K=1,6
                                                                                                                                                                                                                                                                                                                                                                                                                                   NY = NB+LA-LB
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      L (ML,NBA)=5
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    L (ML, NB)=3
                                                                                                                                                                                                                                                                                                                                                                              KB=NB-2*KA
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           L(ML,NB)=2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               KB=NB-2*KA
                                                                                                                                                                                                                                                                                                                       GO TO 109
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              GO TO 151
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         GO TO 719
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          CONTINUE
                                                                                                                                                                                                                                                                                     CONTINUE
                                                                                                                                                                                                                                                                                                                                                            KA=NB/2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             KA=NB/2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                          E=E+1.
RETURN
                                                                                                                                                                                                                                                                                                                                                                                                                   RETURN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                         RETURN
                                                                                                                                                   LA=LAD
                                                                                                                                                                      LB=LBD
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            GAG=1.
RETURN
                                                                                                                                                                                                                                                                                                         7≡6
                                                                                                                                                                                                                                                                                                                                                                                                                                                                          240
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           241
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         110
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    610
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            747
                                                                                                                                                                                                                                                                                                                                                                                                  900
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                    150
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   718
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             109
                                                                                                                                                                                                                                                                                                                                           107
```

```
GIVE BROKEN MOLECULE
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              MOLECULE IS BROKEN, CHECK BOTH DIRECTIONS
                                                                                                                                                                                                                                                                                                                                                                                            C CHECKED IF ADJACENT BOND IS BROKEN TO
                                                                                                                                                                                       IF(L(ML,NLN)-1)132,133,133
                                                                                                                                                                                                                   IF(L(ML,NLN)-2)134,135,120
                                                                                                                                                                                                                                                                                                                                                                                                                                   IF (L(ML,NBA)-1)162,163,163
                                                                                                                                                                                                                                                                                                                                                 IF(L(ML,NBA)-1)155,158,158
                                                                                                                                                                                                                                                                                                                                                                                                                                                                 IF(L(ML,NBA)-2)164,165,166
                                                                                                                                                                                                                                                                                                                                                                             IF(L(ML,NB)-3)650,152,650
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 IF(L(ML,NB)-3)650,152,650
                                                                                                                                                                         NLN=NB+(LA-LB)*KK+(LB-LA)
                                                                                                                                                                                                                                                                                                                                                                                                                        NBA=NB+(LA-LB)*K+LB-LA
                                                                                                                                             K=2*K+LB*(1-KB)+LA*KB
                                                                                                                                                                                                                                                                                                        C VAPORIZED ADJACENT BONDS
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           C VAPORIZED ADJACENT BONDS
             719 CALL MVAP(LA,LB,LC)
C MOLECULE IS BROKEN
                                                       IF(IND)151,151,152
                                                                      IF(K-1)130,130,131
                                                                                                                                                                                                                                                                                                                                   NBA=NB+(LA-LB)*KK
                                                                                                                                                           DO 120 KK=1,K
                                                                                                                                                                                                                                                                                                                      DO 155 KK=1,K
                                                                                                                                                                                                      BVOL=BVOL+1.
                                                                                                                                                                                                                                                                                                                                                                                                           DO 168K=1,KK
                                                                                                                                                                                                                                                                                                                                                                                                                                                   BVOL=BVOL+1.
L (ML, NBA) = 3
                                                                                                                                                                                                                                                              L(ML,NLN)=2
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            L (ML, NBA) =4
                                                                                                                 KB=NB-2*KA
                                                                                                                                                                                                                                IEE=IEE+1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                IEE=IEE+1
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       GO TO 168
                                                                                                                                                                                                                                                                            CONTINUE
                                                                                                                                                                                                                                                                                                                                                                 CONTINUE
                                         NBAA=NBA
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   CONTINUE
                                                                                                   KA=NB/2
                                                                                                                                                                                                                                                E=E+1•
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       E=E+1•
                                                                                    RETURN
                                                                                                                                                                                                                                                                                          RETURN
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              E=E+1•
                                                                                                                               K=K-1
                                                                                                                                                                                                                                                                                                                                                                             620
                                                                     105
                                                                                   130
                                                                                                                                                                                                                                                                            120
                                                                                                                                                                                                                                                                                                                                                   156
                                                                                                   131
                                                                                                                                                                                                    132
                                                                                                                                                                                                                   133
                                                                                                                                                                                                                                 135
134
                                                                                                                                                                                                                                                                                                                      151
                                                                                                                                                                                                                                                                                                                                                                                                                                                  162
                                                                                                                                                                                                                                                                                                                                                                                                                                                                 1.63
                                                                                                                                                                                                                                                                                                                                                               155
                                                                                                                                                                                                                                                                                                                                                                                                                                    161
                                                                                                                                                                                                                                                                                                                                                                                                                                                                               165
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              164
                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        166
168
```

```
070SQU00
-070SQU01
070SQU02
                                                                                                      78
                                                                                                      76
                                                                                                     97 95 --
                                                                                                             2(X)
                                                                                                             6
                                                     LCC=O
NBA=NBAA
CALL MVAP(LA,LB,LCC)
RETURN
END
                                                                                            )1 (X- - (G7
*J -9(NZ5GA.7 -2 -E -G -
*U7(P(ST 9 -G 5484 -1
IF(LA)200,200,201
              LB=0
LCC=67
GO TO 210
                                       LA=0
LB=1
        LA=1
152
                                                                              650
                                                              210
                                       201
```

Security Classification

DOCUMENT CON	TROL DATA - R&	D					
(Security classification of title, body of abstract and indexing annotation must be en ORIGINATING ACTIVITY (Corporate author) Nonmetallic Materials Division, Air Force Materials Laboratory, Research and Technology Division, Air Force Systems Command, Wright-Patterson AFB, Chio							
3. REPORT TITLE THEORETICAL STUDIES ON THE DEGRADATION ization Studies		ymers.	Part II. Vapor-				
4. DESCRIPTIVE NOTES (Type of report and inclusive dates) Summary Report (January 1964 to Decem	ber 1964)						
5. AUTHOR(S) (Last name, first name, initial) Tessler, 1/Lt. Martin M.							
6. REPORT DATE	74. TOTAL NO. OF P	AGES	7b. NO. OF REFS				
8a. CONTRACT OR GRANT NO.	9a. ORIGINATOR'S REPORT NUMBER(S)						
b. PROJECT NO. 7342	ML-TDR-64-151, Part II						
^c Task No. 734203	9b. OTHER REPORT NO(5) (Any other numbers that may be easigned this report)						
d. 10. A VAIL ABILITY/LIMITATION NOTICES							
DISTRIBUTION OF DOCUMENT IS UNLIMIT	CED						
11. SUPPLEMENTARY NOTES	Nonmetallic Materials Division, Air Force Materials Laboratory, Research & Technology Division, Air Force Systems Command, WPAFB,						
The random degradation of four and investigated by means of a digital com	d six-membered	ring la results	dder polymers were compared to a single				

The random degradation of four and six-membered ring ladder polymers were investigated by means of a digital computer and the results compared to a single chain polymer undergoing degradation under identical conditions. The percent vaporization versus time and the rate of weight loss versus time was plotted and significant differences were obtained. The results indicate that ladder polymers should have increased stability over single chain polymers undergoing random degradation.

Security Classification

4.	WEW WARRA	LII	LINK A		LINK B		LINK'C		
	KEY WORDS		ROLE	WT	ROLE	WT.	ROLE	WT	
De	ndder Polymers egradation igital Computer	Studies							
			•						
			·						
								₹ ;	

INSTRUCTIONS

- ORIGINATING ACTIVITY: Enter the name and address of the contractor, subcontractor, grantee, Department of Defense activity or other organization (corporate author) issuing the report.
- 2a. REPORT SECURITY CLASSIFICATION: Enter the overall security classification of the report. Indicate whether "Restricted Data" is included. Marking is to be in accordance with appropriate security regulations.
- 2b. GROUP: Automatic downgrading is specified in DoD Directive 5200.10 and Armed Forces Industrial Manual. Enter the group number. Also, when applicable, show that optional markings have been used for Group 3 and Group 4 as authorized.
- 3. REPORT TITLE: Enter the complete report title in all capital letters. Titles in all cases should be unclassified. If a meaningful title cannot be selected without classification, show title classification in all capitals in parenthesis immediately following the title.
- 4. DESCRIPTIVE NOTES: If appropriate, enter the type of report, e.g., interim, progress, summary, annual, or final. Give the inclusive dates when a specific reporting period is covered.
- 5. AUTHOR(S): Enter the name(s) of author(s) as shown on or in the report. Enter tast name, first name, middle initial. If military, show rank and branch of service. The name of the principal author is an absolute minimum requirement.
- 6. REPORT DATE: Enter the date of the report as day, month, year, or month, year. If more than one date appears on the report, use date of publication.
- 7a. TOTAL NUMBER OF PAGES: The total page count should follow normal pagination procedures, i.e., enter the number of pages containing information.
- 7b. NUMBER OF REFERENCES: Enter the total number of references cited in the report.
- 8a. CONTRACT OR GRANT NUMBER: If appropriate, enter the applicable number of the contract or grant under which the report was written.
- 8b, &c, & 8d. PROJECT NUMBER: Enter the appropriate military department identification, such as project number, subproject number, system numbers, task number, etc.
- 9a. ORIGINATOR'S REPORT NUMBER(S): Enter the official report number by which the document will be identified and controlled by the originating activity. This number must be unique to this report.
- 9b. OTHER REPORT NUMBER(S): If the report has been assigned any other report numbers (either by the originator or by the sponsor), also enter this number(s).
- 10. AVAILABILITY/LIMITATION NOTICES: Enter any limitations on further dissemination of the report, other than those

imposed by security classification, using standard statements such as:

- "Qualified requesters may obtain copies of this report from DDC."
- (2) "Foreign announcement and dissemination of this report by DDC is not authorized."
- (3) "U. S. Government agencies may obtain copies of this report directly from DDC. Other qualified DDC users shall request through
- (4) "U. S. military agencies may obtain copies of this report directly from DDC. Other qualified users shall request through
- (5) "All distribution of this report is controlled. Qualified DDC users shall request through

If the report has been furnished to the Office of Technical Services, Department of Commerce, for sale to the public, indicate this fact and enter the price, if known,

- 11. SUPPLEMENTARY NOTES: Use for additional explana-
- 12. SPONSORING MILITARY ACTIVITY: Enter the name of the departmental project office or laboratory sponsoring (paying for) the research and development. Include address.
- 13. ABSTRACT: Enter an abstract giving a brief and factual summary of the document indicative of the report, even though it may also appear elsewhere in the body of the technical report. If additional space is required, a continuation sheet shall be attached.

It is highly desirable that the abstract of classified reports be unclassified. Each paragraph of the abstract shall end with an indication of the military security classification of the information in the paragraph, represented as (TS), (S), (C), or (U).

There is no limitation on the length of the abstract. However, the suggested length is from 150 to 225 words.

14. KEY WORDS: Key words are technically meaningful terms or short phrases that characterize a report and may be used as index entries for cataloging the report. Key words must be selected so that no security classification is required. Identifiers, such as equipment model designation, trade name, military project code name, geographic location, may be used as key words but will be followed by an indication of technical context. The assignment of links, rules, and weights is optional.